

**PRODUCT-DETAILS** 

## S201P-K6

# Miniature Circuit Breaker - S200P - 1P - K - 6 ampere



#### **General Information**

EAN	4016779592307
Product ID	2CDS281001R0377
Extended Product Type	S201P-K6

Catalog Description

Miniature Circuit Breaker - S200P - 1P - K - 6 ampere

overload protection and the electromechanic tripping mechanism for short circuit protection. They are available in different characteristics (B,C,D,K,Z), configurations (1P,1P+N,2P,3P,3P+N,4P), breaking capacities (up to 25 kA at 230/400 V AC) and rated currents (up to 63A). All MCBs of the product range S200P comply with IEC/EN 60898-1, IEC/EN 609 47-2, UL1077 and CSA 22.2 No. 235, allowing the use for residential,

commercial and industrial applications. Bottom-fitting auxiliary contact can be mounted on S200P to save 50% space.

System pro M compact S200P miniature circuit breakers are current limiting. They have two different tripping mechanisms, the delayed thermal tripping mechanism for

Long Description

#### **Technical**

i cerimicai		
Standards	CSA 22.2 No. 235	
	IEC/EN 60947-2	
	UL 1077	
Number of Poles	1	
Number of Protected	1	
Poles		
Tripping Characteristic		
Rated Current (In)	6 A	
Rated Operational	acc. to IEC 60898-1 230 V AC	
Voltage	acc. to IEC 60947-2 230 V A	
Power Loss	2.4 W	

	at Rated Operating Conditions per Pole 2.4 W
Rated Insulation Voltage (U <sub>i</sub> )	acc. to IEC/EN 60664-1 440 V
Operational Voltage	Maximum (Incl. Tolerance) 253 V AC / 242 V DC Maximum (Incl. Tolerance) 72 V DC
Rated Frequency (f)	50 Hz 60 Hz
Rated Short-Circuit Capacity (I <sub>cn</sub> )	25 kA
Rated Ultimate Short- Circuit Breaking Capacity (I <sub>cu</sub> )	(230 V AC) 25 kA
Rated Service Short-	(230 V AC) 12.5 kA
Circuit Breaking Capacity (I <sub>cs</sub> )	(255 1116) 2216 161
Energy Limiting Class	3
Overvoltage Category	III
Pollution Degree	3
Rated Impulse Withstand Voltage (U <sub>imp</sub> )	4 kV (6.2 kV @ sea level) kV (5.0 kV @ 2000 m) kV
Dielectric Test Voltage	50 / 60 Hz, 1 min: 2 kV
Housing Material	Insulation Group II, RAL 7035
Actuator Type	Insulation group II, black, sealable
Actuator Material	Insulation Group II, Black, Sealable
Actuator Marking	1/0
Contact Position Indication	Red ON / Green OFF
Degree of Protection	IP20
Remarks	IP40 in enclosure with cover
Electrical Endurance	20000 AC cycle
	20000 cycle
Terminal Type	Screw Terminals
Screw Terminal Type	Failsafe Bi-directional Cylinder-lift Terminal
Connecting Capacity	Busbar 10 / 10 mm² Flexible with Ferrule 0.75 16 mm² Flexible 0.75 16 mm² Rigid 0.75 25 mm²
_,,,	Stranded 0.75 25 mm <sup>2</sup>
Tightening Torque  Recommended Screw	2.8 N·m Pozidriv 2
Driver	THE 7 F (25 to 7 F man Materials Dail) and to LEC CO215
Mounting on DIN Rail	TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715 TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715
Mounting Position	Any
Built-In Depth (t <sub>2</sub> )	69 mm
Installation Size  Power Supply Connection	acc. to DIN 43880 1  Arbitrary
Connection	
Environmental  Ambient Air	Operation -25 +55 °C
Temperature	Storage -40 +70 °C
Resistance to Shock acc. to IEC 60068-2-27	25g / 2 shocks / 13 ms
Resistance to Vibrations acc. to IEC 60068-2-6	5g, 20 cycles at 5 150 5 Hz with load 0.8 In
Environmental Conditions	28 cycles with 55 °C / 90-96 %
	and 25 °C / 95-100 %
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment

Technical UL/CSA			
Maximum Operating Voltage UL/CSA	480Y/277 V AG		
Connecting Capacity UL/CSA	Busbar 18-8 AWG Conductor 18-4 AWG		
Tightening Torque UL/CSA	25 in		
Interrupting Rating acc. to UL1077	(277 V AC) 10 kA (480Y / 277 V AC) 10 kA		
Dimensions			
Product Net Width	17.5 mm		
Product Net Depth / Length	69 mm		
Product Net Height	88 mm		
Product Net Weight	0.14 kg		

Container Information	
Package Level 1 Units	10 piece
Package Level 1 Width	92 mm
Package Level 1 Depth / Length	183 mm
Package Level 1 Height	80 mm
Package Level 1 Gross Weight	1.45 kg
Package Level 1 EAN	4016779594943

Ordering	
Minimum Order Quantity	1 piece
Customs Tariff Number	85361010

Certificates and Declarations (Document Nu	mber)
Declaration of Conformity - CE	2CDK403003D0403
Environmental Information	2CDK400030D0201
Instructions and Manuals	2CSC400002D0208
RoHS Information	2CDK403003D0403

Popular Downloads	
Data Sheet, Technical Information	9AKK106930A8017
Instructions and Manuals	2CSC400002D0208

Classifications	
Object Classification	F
Code	

ETIM 6	EC000042 - Miniature circuit breaker (MCB)	
ETIM 7	EC000042 - Miniature circuit breaker (MCB)	
eClass	7.0 27141901	
UNSPSC	39121614	

CASESO   CASES   CAS					Accessories
CMS-101PS Sensor	Jnit Of easure	antity	Type Q	Description	Identifier
CMS-102PS Sensor   CMS-102PS   1	piece	1	CMS-100PS	CMS-100PS Sensor	2CCA880100R0001
S2C-A1 - Shunt Trip   S2C-A1   1	piece	1	CMS-101PS	CMS-101PS Sensor	2CCA880101R0001
S2C-A2 - Shunt Trip   S2C-A2   1	piece	1	CMS-102PS	CMS-102PS Sensor	2CCA880102R0001
S2C-H6R - Auxiliary Contact   S2C-H6R   1	piece	1	S2C-A1	S2C-A1 - Shunt Trip	2CDS200909R0001
S2C-NT - Hand Operated Neutral   S2C-NT   1	piece	1	S2C-A2	S2C-A2 - Shunt Trip	2CDS200909R0002
S2C-S/H6R - Signal / Auxiliary Contact   S2C-S/H6R   1	piece	1	S2C-H6R	S2C-H6R - Auxiliary Contact	2CDS200912R0001
S2C-H11L - Auxiliary Contact   S2C-H11L   1	piece	1	S2C-NT	S2C-NT - Hand Operated Neutral	2CDS200918R0001
2CDS200936R0002         \$2C-H20L - Auxiliary Contact         \$2C-H20L         1           2CDS200936R0003         \$2C-H02L - Auxiliary Contact         \$2C-H02L         1           2CDS200946R0001         \$2C-H6-11R - Auxiliary Contact         \$2C-H6-11R         1           2CDS200946R0002         \$2C-H6-20R - Auxiliary Contact         \$2C-H6-20R         1           2CDS200946R0003         \$2C-H6-02R - Auxiliary Contact         \$2C-H6-02R         1           2CDS200970R0001         \$2C-H01 - Auxiliary Contact         \$2C-H01         1           2CDS200970R0002         \$2C-H10 - Auxiliary Contact         \$2C-H10         1           2CS\$200911R0001         \$2C-UA 12 DC - Undervoltage release         \$2C-UA 12 DC         1           2CS\$200911R0002         \$2C-UA 24 AC - Undervoltage release         \$2C-UA 24 AC         1           2CS\$200911R0003         \$2C-UA 48 AC - Undervoltage release         \$2C-UA 48 AC         1           2CS\$200911R0004         \$2C-UA 230 AC - Undervoltage release         \$2C-UA 230 AC         1           2CS\$200911R0005         \$2C-UA 230 AC - Undervoltage release         \$2C-UA 400 AC         1           2CS\$200911R0006         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 24 DC         1	piece	1	S2C-S/H6R	S2C-S/H6R - Signal / Auxiliary Contact	2CDS200922R0001
2CDS200936R0003         S2C-H02L - Auxiliary Contact         S2C-H02L         1           2CDS200946R0001         S2C-H6-11R - Auxiliary Contact         S2C-H6-11R         1           2CDS200946R0002         S2C-H6-20R - Auxiliary Contact         S2C-H6-20R         1           2CDS200946R0003         S2C-H6-02R - Auxiliary Contact         S2C-H6-02R         1           2CDS200970R0001         S2C-H01 - Auxiliary Contact         S2C-H01         1           2CDS200970R0002         S2C-H10 - Auxiliary Contact         S2C-H10         1           2CSS200911R0001         S2C-UA 12 DC - Undervoltage release         S2C-UA 12 DC         1           2CSS200911R0002         S2C-UA 24 AC - Undervoltage release         S2C-UA 24 AC         1           2CSS200911R0003         S2C-UA 48 AC - Undervoltage release         S2C-UA 48 AC         1           2CSS200911R0004         S2C-UA 230 AC - Undervoltage release         S2C-UA 230 AC         1           2CSS200911R0005         S2C-UA 230 AC - Undervoltage release         S2C-UA 400 AC         1           2CSS200911R0006         S2C-UA 400 AC - Undervoltage release         S2C-UA 24 DC         1           2CSS200911R0007         S2C-UA 24 DC - Undervoltage release         S2C-UA 24 DC         1	piece	1	S2C-H11L	S2C-H11L - Auxiliary Contact	2CDS200936R0001
2CDS200946R0001         \$2C-H6-11R - Auxiliary Contact         \$2C-H6-11R         1           2CDS200946R0002         \$2C-H6-20R - Auxiliary Contact         \$2C-H6-20R         1           2CDS200946R0003         \$2C-H6-02R - Auxiliary Contact         \$2C-H6-02R         1           2CDS200970R0001         \$2C-H01 - Auxiliary Contact         \$2C-H01         1           2CDS200970R0002         \$2C-H10 - Auxiliary Contact         \$2C-H10         1           2CSS200911R0001         \$2C-UA 12 DC - Undervoltage release         \$2C-UA 12 DC         1           2CSS200911R0002         \$2C-UA 24 AC - Undervoltage release         \$2C-UA 24 AC         1           2CSS200911R0003         \$2C-UA 48 AC - Undervoltage release         \$2C-UA 48 AC         1           2CSS200911R0004         \$2C-UA 20 AC - Undervoltage release         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 20 AC - Undervoltage release         \$2C-UA	piece	1	S2C-H20L	S2C-H20L - Auxiliary Contact	2CDS200936R0002
2CDS200946R0002         S2C-H6-20R - Auxiliary Contact         S2C-H6-20R         1           2CDS200946R0003         \$2C-H6-02R - Auxiliary Contact         \$2C-H6-02R         1           2CDS200970R0001         \$2C-H01 - Auxiliary Contact         \$2C-H01         1           2CDS200970R0002         \$2C-H10 - Auxiliary Contact         \$2C-H10         1           2CSS200911R0001         \$2C-UA 12 DC - Undervoltage release         \$2C-UA 12 DC         1           2CSS200911R0002         \$2C-UA 24 AC - Undervoltage release         \$2C-UA 24 AC         1           2CSS200911R0003         \$2C-UA 48 AC - Undervoltage release         \$2C-UA 48 AC         1           2CSS200911R0004         \$2C-UA 110 AC - Undervoltage release         \$2C-UA 230 AC - Undervoltage release         1           2CSS200911R0005         \$2C-UA 230 AC - Undervoltage release         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 24 DC - Undervoltage release	piece	1	S2C-H02L	S2C-H02L - Auxiliary Contact	2CDS200936R0003
2CDS200946R0003         S2C-H6-02R - Auxiliary Contact         S2C-H6-02R         1           2CDS200970R0001         S2C-H01 - Auxiliary Contact         S2C-H01         1           2CDS200970R0002         S2C-H10 - Auxiliary Contact         S2C-H10         1           2CSS200911R0001         S2C-UA 12 DC - Undervoltage release S2C-UA 12 DC         1           2CSS200911R0002         S2C-UA 24 AC - Undervoltage release S2C-UA 24 AC         1           2CSS200911R0003         S2C-UA 48 AC - Undervoltage release S2C-UA 48 AC         1           2CSS200911R0004         S2C-UA 110 AC - Undervoltage release S2C-UA 110 AC         1           2CSS200911R0005         S2C-UA 230 AC - Undervoltage release S2C-UA 200 AC         1           2CSS200911R0006         S2C-UA 400 AC - Undervoltage release S2C-UA 400 AC         1           2CSS200911R0007         S2C-UA 24 DC - Undervoltage release S2C-UA 24 DC         1	piece	1	S2C-H6-11R	S2C-H6-11R - Auxiliary Contact	2CDS200946R0001
2CDS200970R0001         \$2C-H01 - Auxiliary Contact         \$2C-H01         1           2CDS200970R0002         \$2C-H10 - Auxiliary Contact         \$2C-H10         1           2CSS200911R0001         \$2C-UA 12 DC - Undervoltage release         \$2C-UA 12 DC         1           2CSS200911R0002         \$2C-UA 24 AC - Undervoltage release         \$2C-UA 24 AC         1           2CSS200911R0003         \$2C-UA 48 AC - Undervoltage release         \$2C-UA 48 AC         1           2CSS200911R0004         \$2C-UA 110 AC - Undervoltage release         \$2C-UA 230 AC - Undervoltage release         1           2CSS200911R0005         \$2C-UA 230 AC - Undervoltage release         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 400 AC - Undervoltage release         \$2C-UA 24 DC - Undervoltage release         \$2C	piece	1	S2C-H6-20R	S2C-H6-20R - Auxiliary Contact	2CDS200946R0002
2CDS200970R0002         S2C-H10 - Auxiliary Contact         S2C-H10         1           2CSS200911R0001         S2C-UA 12 DC - Undervoltage release         S2C-UA 12 DC         1           2CSS200911R0002         S2C-UA 24 AC - Undervoltage release         S2C-UA 24 AC         1           2CSS200911R0003         S2C-UA 48 AC - Undervoltage release         S2C-UA 48 AC         1           2CSS200911R0004         S2C-UA 110 AC - Undervoltage release         S2C-UA 230 AC - Undervoltage release         S2C-UA 230 AC - Undervoltage release         AC         1           2CSS200911R0006         S2C-UA 400 AC - Undervoltage release         S2C-UA 400 AC - Undervoltage release         AC         1           2CSS200911R0007         S2C-UA 24 DC - Undervoltage release         S2C-UA 24 DC         1	piece	1	S2C-H6-02R	S2C-H6-02R - Auxiliary Contact	2CDS200946R0003
2CSS200911R0001         \$2C-UA 12 DC - Undervoltage release \$2C-UA 12 DC         1           2CSS200911R0002         \$2C-UA 24 AC - Undervoltage release \$2C-UA 24 AC         1           2CSS200911R0003         \$2C-UA 48 AC - Undervoltage release \$2C-UA 48 AC         1           2CSS200911R0004         \$2C-UA 110 AC - Undervoltage release \$2C-UA 110 AC         1           2CSS200911R0005         \$2C-UA 230 AC - Undervoltage release \$2C-UA 230 AC         1           2CSS200911R0006         \$2C-UA 400 AC - Undervoltage release \$2C-UA 400 AC         1           2CSS200911R0007         \$2C-UA 24 DC - Undervoltage release \$2C-UA 24 DC         1	piece	1	S2C-H01	S2C-H01 - Auxiliary Contact	2CDS200970R0001
2CSS200911R0002       \$2C-UA 24 AC - Undervoltage release \$2C-UA 24 AC       1         2CSS200911R0003       \$2C-UA 48 AC - Undervoltage release \$2C-UA 48 AC       1         2CSS200911R0004       \$2C-UA 110 AC - Undervoltage release \$2C-UA 110 AC       1         2CSS200911R0005       \$2C-UA 230 AC - Undervoltage release \$2C-UA 230 AC       1         2CSS200911R0006       \$2C-UA 400 AC - Undervoltage release \$2C-UA 400 AC       1         2CSS200911R0007       \$2C-UA 24 DC - Undervoltage release \$2C-UA 24 DC       1	piece	1	S2C-H10	S2C-H10 - Auxiliary Contact	2CDS200970R0002
2CSS200911R0003         \$2C-UA 48 AC - Undervoltage release \$2C-UA 48 AC         1           2CSS200911R0004         \$2C-UA 110 AC - Undervoltage release \$2C-UA 110 AC         1           2CSS200911R0005         \$2C-UA 230 AC - Undervoltage release AC         1           2CSS200911R0006         \$2C-UA 400 AC - Undervoltage release AC         1           2CSS200911R0007         \$2C-UA 24 DC - Undervoltage release \$2C-UA 24 DC         1	piece	1	S2C-UA 12 DC	S2C-UA 12 DC - Undervoltage release	2CSS200911R0001
2CSS200911R0004         S2C-UA 110 AC - Undervoltage release S2C-UA 110 AC         1           2CSS200911R0005         S2C-UA 230 AC - Undervoltage release AC         1           2CSS200911R0006         S2C-UA 400 AC - Undervoltage release AC         1           2CSS200911R0007         S2C-UA 24 DC - Undervoltage release S2C-UA 24 DC         1	piece	1	S2C-UA 24 AC	S2C-UA 24 AC - Undervoltage release	2CSS200911R0002
2CSS200911R0005         S2C-UA 230 AC - Undervoltage release         S2C-UA 230 AC	piece	1	S2C-UA 48 AC	S2C-UA 48 AC - Undervoltage release	2CSS200911R0003
2CSS200911R0005 S2C-UA 230 AC - Undervoltage release AC 1 2CSS200911R0006 S2C-UA 400 AC - Undervoltage release S2C-UA 400 AC 1 2CSS200911R0007 S2C-UA 24 DC - Undervoltage release S2C-UA 24 DC 1	piece	1	2C-UA 110 AC	S2C-UA 110 AC - Undervoltage releases	2CSS200911R0004
2CSS200911R0006 S2C-UA 400 AC - Undervoltage release AC 1 2CSS200911R0007 S2C-UA 24 DC - Undervoltage release S2C-UA 24 DC 1	piece	1		S2C-UA 230 AC - Undervoltage release	2CSS200911R0005
	piece	1		S2C-UA 400 AC - Undervoltage release	2CSS200911R0006
2CSS200911R0008	piece	1	S2C-UA 24 DC	S2C-UA 24 DC - Undervoltage release	2CSS200911R0007
	piece	1	S2C-UA 48 DC	S2C-UA 48 DC - Undervoltage release	2CSS200911R0008
2CSS200911R0009 S2C-UA 110 DC - Undervoltage releaseS2C-UA 110 DC 1	piece	1	2C-UA 110 DC	S2C-UA 110 DC - Undervoltage releaseS	2CSS200911R0009
2CSS200911R0010 S2C-UA 230 DC - Undervoltage release S2C-UA 230 DC 1	piece	1		S2C-UA 230 DC - Undervoltage release	2CSS200911R0010
2CSS200998R0001 S2C-BP - Mechanical tripping device S2C-BP 1	piece	1	S2C-BP	S2C-BP - Mechanical tripping device	2CSS200998R0001
2CSS200999R0001 S2C-EST - Plug-in base S2C-EST 1	piece	1	S2C-EST	S2C-EST - Plug-in base	2CSS200999R0001
2CSS201997R0013 S2C-CM1 - Motor operating device S2C-CM1 1	piece	1	S2C-CM1	S2C-CM1 - Motor operating device	2CSS201997R0013
2CSS203997R0013 S2C-CM2/3 - Motor operating device S2C-CM2/3 1	piece	1	S2C-CM2/3	S2C-CM2/3 - Motor operating device	2CSS203997R0013
2CSS204997R0013 S2C-CM4 - Motor operating device S2C-CM4 1	piece	1	S2C-CM4	S2C-CM4 - Motor operating device	2CSS204997R0013
GHS2001901R0003 S2C-DH - Mechanical Accessories S2C-DH 1	piece	1	S2C-DH	S2C-DH - Mechanical Accessories	GHS2001901R0003

### Categories

S201P-K6 5

