

# VGA to Video Converter

pro-SIGNAL

RoHS  
Compliant



## Description

This VGA to BNC converter also features a VGA output port that allows for VGA Loop-Through. You can simultaneously view video on a VGA monitor while viewing the video on your CRT ,TV monitor. It convert your VGA signal to be viewed on any TV, projector, or any other viewing device that uses standard BNC (RCA) connector with this simple external device.

## Features

- Use TV as PC monitors to view presentations, games, pictures and movies or browse the Web.
- Connects your DVR with VGA output port to existing TV or CRT monitor.
- Ideal for notebook computer users to easily connect and use a large-format monitor.
- Video standards: NTSC/NTSC-EIAJ/PAL/PAL-M/PAL-N.
- Resolutions support: 640 x 480 (up to 85 Hz), 800 x 600 (up to 85 Hz) and 1024 x 768 (up to 75 Hz).
- Input port: VGA (DB15).
- Dual output ports: composite video (BNC connector), VGA (DB15).
- Image controls: Horizontal and vertical size, brightness, contrast, hue, saturation, sharpness and on screen display background.
- Simple and quick to install; Windows and Mac compatible.
- No driver or operating system requirements; compatible with Windows and Mac computers.

## Specifications

Input Signal	VGA x1
Output Signal	Composite Video (BNC) x 1, VGA X1 15 pin D female connector
Power Consumption	500mA
Power Supply	DC5V 1Amp Regulated Power Supply
Temperature	Operation: 0°C to +55°C, Storage: -20°C TO 85°C, Humidity: up to 95%
Dimensions	125mm x 95mm x 30mm
Weight	265g

## Part Number Table

Description	Part Number
VGA to Video Converter with 1× VGA Socket to 1× VGA Socket & 1x BNC Socket	PSG08196

**Important Notice :** This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. pro-SIGNAL is the registered trademark of Premier Farnell Limited 2019.

Newark.com/exclusive-brands  
Farnell.com/exclusive-brands  
Element14.com/exclusive-brands

pro-SIGNAL