

RF Inductor-Wirewound



BWS20JRF0-KIT JIS 2012 Size

Designer Kit Contents

Pulse - Std Power Part Number	L (mm)	W(mm)	T (mm)	SIZE Code (JIS/EIA)	Inductance (nH)	Tolerance (±%)	RDC(Ω) Max.	IDC(mA)Max.	Quantity
BWCS002317152N7J00	2.3	1.7	1.5	2012/0805	2.7	5	0.06	800	20
BWCS002317152N8J00	2.3	1.7	1.5	2012/0805	2.8	5	0.06	800	20
BWCS002317153N0J00	2.3	1.7	1.5	2012/0805	3	5	0.06	800	20
BWCS002317153N3J00	2.3	1.7	1.5	2012/0805	3.3	5	0.08	600	20
BWCS002317155N6J00	2.3	1.7	1.5	2012/0805	5.6	5	0.08	600	20
BWCS002317156N8J00	2.3	1.7	1.5	2012/0805	6.8	5	0.11	600	20
BWCS002317157N5J00	2.3	1.7	1.5	2012/0805	7.5	5	0.14	600	20
BWCS002317158N2J00	2.3	1.7	1.5	2012/0805	8.2	5	0.12	600	20
BWCS0023171510NJ00	2.3	1.7	1.5	2012/0805	10	5	0.1	600	20
BWCS0023171512NJ00	2.3	1.7	1.5	2012/0805	12	5	0.15	600	20
BWCS0023171515NJ00	2.3	1.7	1.5	2012/0805	15	5	0.17	600	20
BWCS0023171518NJ00	2.3	1.7	1.5	2012/0805	18	5	0.2	600	20
BWCS0023171522NJ00	2.3	1.7	1.5	2012/0805	22	5	0.22	500	20
BWCS0023171524NJ00	2.3	1.7	1.5	2012/0805	24	5	0.22	500	20
BWCS0023171527NJ00	2.3	1.7	1.5	2012/0805	27	5	0.25	500	20
BWCS0023171533NJ00	2.3	1.7	1.5	2012/0805	33	5	0.27	500	20
BWCS0023171536NJ00	2.3	1.7	1.5	2012/0805	36	5	0.27	500	20
BWCS0023171539NJ00	2.3	1.7	1.5	2012/0805	39	5	0.29	500	20
BWCS0023171543NJ00	2.3	1.7	1.5	2012/0805	43	5	0.34	500	20
BWCS0023171547NJ00	2.3	1.7	1.5	2012/0805	47	5	0.31	500	20
BWCS0023171556NJ00	2.3	1.7	1.5	2012/0805	56	5	0.34	500	20
BWCS0023171568NJ00	2.3	1.7	1.5	2012/0805	68	5	0.38	500	20
BWCS0023171582NJ00	2.3	1.7	1.5	2012/0805	82	5	0.42	400	20
BWCS0023171591NJ00	2.3	1.7	1.5	2012/0805	91	5	0.48	400	20
BWCS00231715R10J00	2.3	1.7	1.5	2012/0805	100	5	0.46	400	20
BWCS00231715R11J00	2.3	1.7	1.5	2012/0805	110	5	0.48	400	20
BWCS00231715R12J00	2.3	1.7	1.5	2012/0805	120	5	0.51	400	20
BWCS00231715R15J00	2.3	1.7	1.5	2012/0805	150	5	0.56	400	20
BWCS00231715R18J00	2.3	1.7	1.5	2012/0805	180	5	0.64	400	20
BWCS00231715R20J00	2.3	1.7	1.5	2012/0805	200	5	0.68	400	20
BWCS00231715R22J00	2.3	1.7	1.5	2012/0805	220	5	0.7	400	20
BWCS00231715R24J00	2.3	1.7	1.5	2012/0805	240	5	1	350	20
BWCS00231715R25J00	2.3	1.7	1.5	2012/0805	250	5	1.2	350	20
BWCS00231715R27J00	2.3	1.7	1.5	2012/0805	270	5	1	350	20
BWCS00231715R30J00	2.3	1.7	1.5	2012/0805	300	5	1.4	310	20
BWCS00231715R33J00	2.3	1.7	1.5	2012/0805	330	5	1.4	310	20
BWCS00231715R39J00	2.3	1.7	1.5	2012/0805	390	5	1.5	290	20
BWCS00231715R47J00	2.3	1.7	1.5	2012/0805	470	5	1.76	250	20
BWCS00231715R51J00	2.3	1.7	1.5	2012/0805	510	5	1.9	230	20
BWCS00231715R56J00	2.3	1.7	1.5	2012/0805	560	5	1.9	230	20
BWCS00231715R62J00	2.3	1.7	1.5	2012/0805	620	5	2.2	210	20
BWCS00231715R68J00	2.3	1.7	1.5	2012/0805	680	5	2.2	190	20
BWCS00231715R82J00	2.3	1.7	1.5	2012/0805	820	5	2.35	180	20
BWCS00231715R0J00	2.3	1.7	1.5	2012/0805	1000	5	2.5	170	20
BWCS00231715R2J00	2.3	1.7	1.5	2012/0805	1200	5	2.5	170	20
BWCS00231715R8J00	2.3	1.7	1.5	2012/0805	1800	5	2.5	170	20
BWCS002317152R2J00	2.3	1.7	1.5	2012/0805	2200	5	3.9	140	20
BWCS002317153R3J00	2.3	1.7	1.5	2012/0805	3300	5	4.4	90	20
BWCS002317154R7J00	2.3	1.7	1.5	2012/0805	4700	5	6.4	90	20
BWLS0024171578NJ00	2.4	1.7	1.5	2012/0805	0.078	5	0.06	2000	20

RF Inductor-Wirewound



BWS20JRF0-KIT JIS 2012 Size

Designer Kit Contents

Pulse - Std Power Part Number	L (mm)	W(mm)	T (mm)	SIZE Code (JIS/EIA)	Inductance (nH)	Tolerance (±%)	RDC(Ω) Max.	IDC(mA)Max.	Quantity
BWLS00241715R11J00	2.4	1.7	1.5	2012/0805	0.11	5	0.07	2000	20
BWLS00241715R47J00	2.4	1.7	1.5	2012/0805	0.47	5	0.4	800	20
BWLS00241715R56J00	2.4	1.7	1.5	2012/0805	0.56	5	0.4	800	20
BWLS00241715R68J00	2.4	1.7	1.5	2012/0805	0.68	5	0.4	800	20
BWLS00241715R91J00	2.4	1.7	1.5	2012/0805	0.91	5	0.69	700	20
BWLS002417151R0J00	2.4	1.7	1.5	2012/0805	1	5	0.69	700	20
BWLS002417151R2J00	2.4	1.7	1.5	2012/0805	1.2	5	0.83	700	20
BWLS002417151R5J00	2.4	1.7	1.5	2012/0805	1.5	5	0.83	700	20
BWLS002417151R8J00	2.4	1.7	1.5	2012/0805	1.8	5	1	650	20
BWLS002417152R2J00	2.4	1.7	1.5	2012/0805	2.2	5	1.1	650	20
BWLS002417152R7J00	2.4	1.7	1.5	2012/0805	2.7	5	1.25	650	20
BWLS002417153R3J00	2.4	1.7	1.5	2012/0805	3.3	5	1.45	650	20
BWLS002417153R9J00	2.4	1.7	1.5	2012/0805	3.9	5	1.5	600	20
BWLS002417154R7J00	2.4	1.7	1.5	2012/0805	4.7	5	1.6	530	20
BWLS002417155R6J00	2.4	1.7	1.5	2012/0805	5.6	5	1.7	500	20
BWLS002417156R8J00	2.4	1.7	1.5	2012/0805	6.8	5	1.95	470	20
BWLS002417158R2J00	2.4	1.7	1.5	2012/0805	8.2	5	2.1	450	20
BWLS00241715100J00	2.4	1.7	1.5	2012/0805	10	5	2.4	400	20
BWLS00241715120J00	2.4	1.7	1.5	2012/0805	12	5	3.2	360	20
BWLS00241715150J00	2.4	1.7	1.5	2012/0805	15	5	3.55	350	20
BWLS00241715180J00	2.4	1.7	1.5	2012/0805	18	5	4.9	300	20
BWLS00241715220J00	2.4	1.7	1.5	2012/0805	22	5	5.45	270	20
BWLS00241715270J00	2.4	1.7	1.5	2012/0805	27	5	7.8	240	20
BWLS00241715330J00	2.4	1.7	1.5	2012/0805	33	5	9.5	210	20
BWLS00241715470J00	2.4	1.7	1.5	2012/0805	47	5	14.5	180	20

RF Inductor-Wirewound



BWS20JRF0-KIT JIS 2012 Size

Dimensions – Millimeters (Inches)

