

Security Light Switch



Description:

A 24 hour/7 day digital security light switch which will automatically turn filament, fluorescent, low energy and low voltage lights ON & OFF at pre-programmed times. A total of 6 ON and 6 OFF independent switching commands can be set to operate over all 7 days (24 hour operation) or on individual days. An optional dusk start feature turns lights ON at dusk and OFF at a programmed time.

Features:

- Simple to programme and operate
- 6 ON/OFF switching programmes
- Three position slide switch allows manual operation, auto operation with timed ON and OFF or auto and photocell operation giving dusk start and timed OFF with additional timed ON
- In built 1000 hours rechargeable battery retains programmes and clock times during power failure
- Replaces any conventional single gang (ON/OFF & 2 way) light switch.
- Slim and tidy with concealed front panel
- Controls up to 300W of filament lighting
- Can also be used as a normal ON/OFF switch

Specifications:

Controller Output	: Digital
Time Range	: 24h / 7day
Battery Life (Working)	: 1,000h
Colour	: White
Contact Type	: ON/OFF
External Depth	: 50mm
External Length / Height	: 86mm
External Width	: 86mm
For Use With	: Low Energy, Fluorescent and Low Voltage Lighting
Output Type	: Digital
Switch type	: Single or Double Gang Single
Maximum lamp size	: 40W minimum up to maximum 300W
Light level sensing	: Yes
Light on time adjustable	: Yes
Concealed front panel	: Yes
Fluorescent and low energy lighting	: 20W or 25W low energy lamp 76W fluorescent 200W low voltage
Conforms to directives	: 73/23/EEC; 89/336/EEC

Note: Cannot be used with dimmer switches in two way switching system or replace an intermediate switch in three or more way switching system.

ZV700 is suitable for low energy, fluorescent and low voltage lighting.

Part Number Table

Description	Part Number
Security Light Switch, Digital	ZV700

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.