



### Main

Product or component type	Communication card
Range compatibility	Altivar 61 Altivar 71 Altivar 61Q Altivar 71Q
Communication port protocol	Interbus
Connector type	9-way female SUB-D connector 9-way male SUB-D connector

### Complementary

Communication service	Abort communication relationship Communication and drive status Communication monitoring I/O data Identification of the card Initialize communication relationship Profile 21 Read object description Read parameter Write parameter
Supply	By drive but necessary to use an external supply if the inverter is not powered
Display type	1 LED for BA (periodic data) 1 LED for RC (bus input) 1 LED for Rd (bus output) 1 LED for TR (messaging) 1 LED for U (power supply) Graphic display terminal for control word received Graphic display terminal for reference received
Product weight	0.3 kg

### Environment

### Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.