



MP730988

MP730989

Features

Display Count	: 9999
Auto Range	: √
REL	: √
NCV	: √
Diode	: √
Continuity Test	: √
Acousto-optic Indication (NCV/Continuity/Battery Power)	: √
Low Battery Indication	: ≤3.6V
Data Hold	: √
Auto Power Off	: 15 Min.
Operating Temperature	: 0°C to +40°C
Safety	: CATII 1000V / CATIII 600V

Applications

Test & Measurement, Electronics Service, Industrial & Manufacturing, Automotive, Electrical

Specifications

Certificates	: CE, UKCA, cETLus
DC Voltage	: 1000V ±(0.5%+3)
AC Voltage	: 1000V ±(0.8%+3)
DC Current	: 10A ±(0.8%+3)
AC Current	: 10A ±(1%+3)
Resistance	: 100MΩ ±(0.8%+2)
Capacitance	: 10mF, 100mF (MP730989 only) ±(4%+5)
Frequency	: 99.99Hz to 9.999MHz ±(0.1%+5)
Duty Cycle	: 0.1% to 99.9% ±(3%+5)
Temperature	: -40°C to +1000°C /-40°F to 1832°F (±4°C/±5°F)

Accessories	Qty.	Note
Operating Manual	1 piece	-
Test Leads	MP730988	1 pair Leads length: 900mm, Rod length: 101mm; Tip length: 16.5mm Safety level: CAT I 1000V/CAT II 600V 10A
	MP730989	1 pair Leads length: 900mm, Rod length: 115mm; Tip length: 18mm Safety level: CAT III 1000V/CAT IV 600V 10A
Temp Probe	1 piece	Cross point thin line 1000 K type
Battery	3 pieces	1.5V AAA × 3, Replaceable

Part Number Table

Description	Part Number
Digital Multimeter 9999count, True RMS, CATII1000/CATIII600V, with Rotary handle design	MP730988
Digital Multimeter 9999count, True RMS, CATII1000/CATIII600V, with push-button design	MP730989

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.