# Programmable Linear Bench Top DC Power Supplies



### RoHS Compliant



### **Description**

This series DC power supply with three independent outputs is a cost-effective programmable DC power supply with excellent performance, reliable output and clear interface.

The instrument has constant voltage (CV) and constant current (CC) modes, short-circuit and over-voltage protection functions, which can perfectly meet various test requirements.

#### **Features**

- Maximum power up to 373W
- Four channel independent output: CH1/CH2: 0~30V/5A,CH3: 0~6V/3A, CH4: 5V/ 2A
- Multiple protection: 0CP/0VP/0TP
- · Excellent load regulation and line regulation
- Ultra low output ripple and noise
- · Support one key serial and parallel output function
- The 4.3-inch TFT display can display three channels and multiple parameters at the same time
- · List / delayer function to control voltage and current output as required
- · External trigger function to realize industrial automation control
- · Provide USB host, USB device, LAN, RS232, digital I0 and other interfaces
- · With waveform display function, real-time and dynamic display of output voltage / current / power waveform
- · Intelligent speed control of fan can effectively reduce fan noise during operation
- · Support 10 groups of file storage and transfer out, and support USB flash disk reading and writing
- High precision display of five-digit voltage / four-digit current, with resolutions of 10mV / 1mA and 1mV / 1mA
- · Keyboard lock function to prevent misoperation
- · Support SCPI remote command control

### **Specifications**

Channel	Channel	4
Output Rating	Voltage	CH1&CH2: 0-32V
		CH3: 0~6V
		CH4: 5V (USB Output )
	Current	CH1&CH2: 0~5A
		CH3: 0~3A
		CH4: 2A (USB Output)
	Power	348W
CV mode	Regulation	Line Regulation: <0.01%+2mV
		Load Regulation: <0.01%+2mV
	Regulation	<350µVrms/ 2mVpp(5Hz~1MHz)
	Reaction time	≤50µs (50% load variation,minimumload 0.5A)
	Command processing time	<100ms

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro



# Programmable Linear Bench Top DC Power Supplies



CC mode	B 1.6	Line Regulation: ≤0.01%+250µA
	Regulation	Line Regulation: ≤0.01%+250µA
	Ripple current	≤2mArms
Tracking mode		Line Regulation: ≤0.01%+2mV
	parallel connection	Load Regulation: ≤0.01%+2mV
	series connection	Line Regulation: ≤0.01%+3mV
		Load Regulation: <300mV
	Tracking error	≤0.5%+10mV (10-30V No load)
		≤0.5%+30mV (0-9.99V No load)
		Access load < 300mA
	B: 1	Voltage full scale, A-digit display: 4.3inchLCD
	Display	Current full scale, A-digit display; 4.3 inchLCD
	Dan managin na anaghatian	Voltage:10mV
	Programming resolution	Current: 1mA
	B "	Voltage: 10mV
Measure	Readback resolution	Current: 1mA
	. (05.500)	Voltage: ± (0.3%+20mV)
	Programming accuracy (25±5°C)	Current: ± (0.2%+5mA)
	Doodhack convery (2515°C)	Voltage: ± (0.1%+20mV)
	Readback accuracy (25±5°C)	Current: ± (0.15%+5mA)
	CHA	Rise: full load < 50ms;Noload < 30ms
	CH1	Fall: full load < 45ms; No load < 400ms
Voltage programmed speed	CHO	Rise: full load < 50ms; No load < 30ms
(1% of the total variation range)	CH2	Fall: full load < 45ms; No load < 400ms
	CH2	Rise: full load < 15ms: No load <13ms
	CH3	Fall: full load < 22ms; No load <100ms
	CUIA	Voltage: 0.01%+5mV
	CH1	Current: 0.01%+2mA
Temperature coefficient per C° (output percentage + offset)	CHO	Voltage: 0.01%+5mV
	CH2	Current: 0.01%+2mA
	СНЗ	Voltage: 0.01%+2mV
	СПЗ	Current: 0.01%+2mA
	Output voltage	5V ±0.25V
Channel 4 (USB output)	Output current	2A
Input	Voltage	AC100V/120V/220V/230V ±10%
	Frequency	50/60Hz
	Power	MAX 600W
	Fuse	AC220V : T4AL250V
		ACT10V: T8AL250V

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro



# Programmable Linear Bench Top DC Power Supplies



Environment	Operating temperature	0°C to 40°C
	Operating humidity	20%~80% (non-condensing)
	Storage temperature	-10°C to 60°C
	Altitude	≤2000m
	Pollution degree	2
Size and weight	Size	355mm × 240mm × 168mm
	Weight	10.2kg
Warranty	03 years	

#### **Part Number Table**

Description	Part Number
Programmable Linear Bench Top DC Power Supplies, 4 CH, EU/UK	MP711001

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

