



#### **Product features**

- Perfect for decorative and general lighting applications and creates a warm ambience similar to traditional lamps
- The versatile  $\dot{\text{ToLEDo}}$  Retro ball range is the ideal replacement for halogen and incandescent lamps and perfect for chandeliers and decorative applications
- Same look, size and functionality as incandescent lamps
- Omni-directional light distribution
- Gives same sparkling light effect as the incandescent lamp
- Dimensionally identical to incandescent lamps fits all fixtures
- Environment-friendly no mercury and lower CO2 emissions











### PRODUCT OVERVIEW

Product name	ToLEDo RT Ball V5 CL 250LM 827 E14 SL
Technology	LED
Watt (Rated) (W)	2.5
Туре	LED exchangeable
Cap/Base	E14
Fixture rating	Open
General application	Hospitality, Residential & Consumer
ETIM Class	EC001959
E-number FI	4740947
Warranty	3 years
Luminous flux (Im)	250
Colour temperature (K)	2700
Light colour	Homelight
CRI (Ra)	80
Colour Variation Initial (SDCM)	SDCM6
Photobiological Risk Group	RG1
Wattage (W)	2.5
Product Voltage (V)	230
Dimmable	No
Average life (Nominal) (h)	15000
Product EAN number	5410288294995

### **DATA TABLE**

Genera	ıl data
Genera	II uata

**Product name** ToLEDo RT Ball V5 CL 250LM 827 E14 SL



Tachnalagy	LED
Technology	LED
Watt (Rated) (W)	2.5
Type Cap/Base	LED exchangeable E14
Fixture rating	
<u> </u>	Open Hospitality, Residential & Consumer
General application	-20°C - 40°C
Operating temperature range (°C) Performance ambient temperature Tq	
(°C)	25
ETIM Class	EC001959
E-number FI	4740947
Warranty	3 years
Optical data	
Luminous flux (Im)	250
Luminous flux (Rated) (Im)	250
Colour temperature (K)	2700
Light colour	Homelight
CRI (Ra)	80
Colour Variation Initial (SDCM)	SDCM6
Photobiological Risk Group	RG1
Lumen maintenance at end of nominal life (%)	70
. ( .)	
Electrical data	
Electrical data  Wattage (W)	2.5
	2.5 25
Wattage (W)	-
Wattage (W) Equivalent watt (W)	25
Wattage (W) Equivalent watt (W) Product Voltage (V)	25 230
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature	25 230 No
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures	25 230 No >50000
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required	25 230 No >50000
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable	25 230 No >50000 No No
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A)	25 230 No >50000 No No 5.9
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs)	25 230 No >50000 No No 5.9 180
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class)	25 230 No >50000 No No 5.9 180 F
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz)	25 230 No >50000 No No 5.9 180 F 50/60Hz
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz) Max. Luminaires per 16A C Breaker	25 230 No >50000  No No 180 F 50/60Hz 27
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz) Max. Luminaires per 16A C Breaker Max. Luminaires per 16A B Breaker Lifetime data	25 230 No >50000  No No 180 F 50/60Hz 27 14
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz) Max. Luminaires per 16A C Breaker Max. Luminaires per 16A B Breaker Lifetime data Lifespan L70 B50	25 230 No >50000  No No 180 F 50/60Hz 27 14
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz) Max. Luminaires per 16A C Breaker Max. Luminaires per 16A B Breaker Lifetime data Lifespan L70 B50 Average life (Nominal) (h)	25 230 No >50000  No No S.9 180 F 50/60Hz 27 14
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz) Max. Luminaires per 16A C Breaker Max. Luminaires per 16A B Breaker Lifetime data Lifespan L70 B50	25 230 No >50000  No No 180 F 50/60Hz 27 14
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz) Max. Luminaires per 16A C Breaker Max. Luminaires per 16A B Breaker Lifetime data Lifespan L70 B50 Average life (Nominal) (h)	25 230 No >50000  No No S.9 180 F 50/60Hz 27 14
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz) Max. Luminaires per 16A C Breaker Max. Luminaires per 16A B Breaker Lifetime data Lifespan L70 B50 Average life (Nominal) (h) Average life (Rated) (h)	25 230 No >50000  No No 180 F 50/60Hz 27 14  15000 15000
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz) Max. Luminaires per 16A C Breaker Max. Luminaires per 16A B Breaker Lifetime data Lifespan L70 B50 Average life (Nominal) (h) Average life (Rated) (h) Physical data Nominal Product Length (mm)	25 230 No >50000  No No 180 F 50/60Hz 27 14  15000 15000 15000
Wattage (W) Equivalent watt (W) Product Voltage (V) Control gear required No. Of switching cycles before premature failures Transformer required Dimmable Inrush Current (A) Inrush Duration (µs) Lamp Energy Label (class) Nominal Frequency (Hz) Max. Luminaires per 16A C Breaker Max. Luminaires per 16A B Breaker Lifetime data Lifespan L70 B50 Average life (Nominal) (h) Average life (Rated) (h)	25 230 No >50000  No No 180 F 50/60Hz 27 14  15000 15000




### Packaging

Single packaging type	Carton
Product EAN number	5410288294995
Packaging single length / height (cm)	9.5
Packaging single width (cm)	5.0
Packaging single depth (cm)	5.0
DUN14 (outer)	15410288294992
Units per outer package	6
Packaging outer length / height (cm)	15.8
Packaging outer width (cm)	10.7
Packaging outer depth (cm)	10.5

### Safety data

Optimal operating condition (°C)	-20-40
Breakage cleaning instructions	Not applicable
Special purpose lamp	No
Dry applications use only	Yes
Suitable for household illumination	Yes
Safety message	Not Suitable for totally enclosed fixtures

### **PHOTOMETRY**



### **TECHNICAL DRAWINGS**

