

Digital AC Millivoltmeter **multicomp** PRO

RoHS
Compliant



Description

This series digital AC millivolt meter are applied to measure Sine signal with AC voltage range from 50 μ V to 400V and frequency range from 5Hz to 6MHz. It is necessary basic instrument to measure and test voltage.

Application

Factory, Lab, R&D institution, Troops, Colleges and Universities

Features

- LED display, dual independent channels
- Auto/Manual ranging can be selected.
- Multi display result with different units.
- Standard interface USB device and optional LAN interface

Specification

MP700968	
Frequency Range	5Hz ~ 6MHz
Measurement Range	
AC Voltage	50 μ V ~ 300V
Scale	3mV, 30mV, 300mV, 3V, 30V, 300V
dBV	-86dBV ~ 50dBV
dBm	-73dbm ~ 62.55dbm (R=50 Ω) -84dbm ~ 51.76dbm (R=600 Ω)
Vpp	141 μ V ~ 848.4Vpp
dB	-86dB~49.54dB
Voltage Measurement Error	
\geq 5Hz ~ 100Hz	\pm 2.5% reading \pm 0.8% range
>100Hz ~ 500kHz	\pm 1.5% reading \pm 0.5% range
>500kHz ~ 2MHz	\pm 2% reading \pm 1% range
>2MHz ~ 3MHz	\pm 3% reading \pm 1% range
>3MHz ~ 5MHz	\pm 4% reading \pm 2% range
>5MHz ~ 6MHz	\pm 5% reading \pm 4% range

Newark.com/multicomp-pro
Farnell.com/multicomp-pro
sg.element14.com/b/multicomp-pro

multicomp PRO

Digital AC Millivoltmeter **multicomp** PRO

MP700968	
Resolution	
Range	4 1/2 digits Display
3mV	0.0001mV
30mV	0.001mV
300mV	0.01mV
3V	0.0001V
30V	0.001V
300V	0.01V
Maximum Undamaged Input Voltage	
Range:300V	350Vrms
General Characteristics	
Power	AC220 (1±10%)V, 50 (1±5%)Hz, < 20VA
Interface	USB Device
Dimension & Weight	260mm × 106mm × 375 mm, Approx.3.9 kg
Display	LED Display
Warranty	03 years

Part Number Table

Description	Part Number
Digital AC Millivoltmeter, 5Hz to 6MHz	MP700968

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro
 Farnell.com/multicomp-pro
 sg.element14.com/b/multicomp-pro

multicomp PRO