

# Cat. 5E RJ45 Wall Outlet Module - 70402

## Wiring Instructions

Please note: there are 2 wiring standards for networking T568A & T568B.

If adding to an existing network check the existing wiring to determine the standard used and wire accordingly.  
If wiring a new network use T568B.


1. Strip 75mm (3") of cable jacket, position first pair of wires according to colour code and insert wires. Remember to untwist each pair of wires only as much as is needed to make a strain free connection. Running wires along the central channel lets you preserve wire twisting as close to termination as possible.

2. Repeat Step 1 for each subsequent pair until all four pairs of wires are terminated. The module can now be snapped into a suitable faceplate.


	258A/EIA-T568B	EIA-T568A
1	White/Orange	White/Green
2	Orange	Green
3	White/Green	White/Orange
4	Blue	Blue
5	White/Blue	White/Blue
6	Green	Orange
7	White/Brown	White/Brown
8	Brown	Brown

### Step 1

Use impact/punchdown tool to insert wires



### Step 2



**PHILEX**

**CUSTOMER CARELINE: 0901 293 0038**

Calls are charged at £1 per minute from a BT landline

Call charges from other networks may vary

**TECHNICAL SUPPORT: <http://technical.philex.com>**

© Philex Electronic Ltd. 2010. v1.7  
MK42 ONX [www.philex.com](http://www.philex.com)