Bipolar Transistor




RoHS





Compliant



Description:

A epitaxial silicon PNP planar transistor in a TO-39 type package designed for use as drivers for high power transistors in general purpose amplifier and switching circuits.

Maximum Ratings:

Characteristic	Symbol	Rating	Unit	
Collector - Emitter Voltage	V _{CEO}	- 80		
Collector - Base Voltage	l I _E	00	V	
Emitter - Base Voltage		7		
Collector Current	I _C	1	A	
Base Current	l I _B	200	mA	
Total Device Dissipation ($T_c = +25^{\circ}C$)		6	W	
Total Device Dissipation($T_A = +25^{\circ}C$)	P _{tot}	1		
Operating Junction Temperature	TJ	-65 to +200	°C	
Storage Temperature Range	T _{stg}	-03 10 +200		
Thermal Resistance, Junction-to-Case	R _{thJC}	29	°C/W	

www.element14.com www.farnell.com www.newark.com






Parameter	Symbol	Test Conditions	Min	Max	Unit
	I _{CBO}	V _{CB} = 80V, I _E = 0		100	μA
Collector Cutoff Current	I _{CEO}	V _{CE} = 60V, I _B = 0		1	mA
Collector Cutoff Current	I _{CEV}	V _{CE} = 80V, V _{BE} = -1.5V	-	0.1	μA
		V _{CE} = 60V, V _{BE} = -1.5V, T _C = +150°C		1	mA
Emitter Cutoff Voltage	I _{EBO}	V _{EB} = 7V, I _C = 0		500	μA
Collector - Emitter Sustaining Voltage	V _{CEO(sus)}	I _C = 100mA, I _B = 0, (Note1)	80	-	
Collector - Emitter Saturation Voltage	V _{CE(sat)}	I _C = 1A, I _B = 125mA, (Note1)		0.6	V
Base-Emitter On Voltage	V _{BE}	V _{CE} = 1V, I _C = 250mA	-	1	
DC Current Gain	h	I _C = 250mA, V _{CE} = 2V, (Note 1)	30	150	
DC Current Gain	h _{FE}	I _C = 1A, V _{CE} = 1V, (Note 1)	10		-
Transition Frequency	f _t	V _{CE} = 10V, I _C = 100mA, f = 1MHz	3	-	MHz
Collector - Base Capactiance	C _{cbo}	V _{CB} = 10V, I _E = 0, f = 0.1MHz	-	100	pF
Small - Signal Current Gain	h _{fe}	V _{CE} = 10V, I _C = 50mA, f = 1kHz	25	-	-

Electrical Characteristics: (T_A = +25°C Unless otherwise specified)

Note:

1. Pulse Duration : \leq 300µs, Duty Cycle \leq 2%



Dimensions	Α	В	С	D	Е	F	G	Н	Ι	J	к
Min.	8.5	7.74	6.09	0.4	-	2.41	4.82	0.71	0.73	12.7	42°
Max.	9.39	8.5	6.6	0.53	0.88	2.66	5.33	0.86	1.02	-	48°

Dimensions : Millimetres

Pin Configuration:

- Emitter
 Base
- 3. Collector

Part Number Table

Description	Part Number			
Transistor, PNP, 3A, 80V, TO-39	2N4236			

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com

