Crimp Housing






Specifications:


 $\begin{array}{lll} \text{Current Rating} & : 3\text{A AC/DC} \\ \text{Voltage Rating} & : 250\text{V AC/DC} \\ \text{Contact Resistance} & : 15\text{m}\Omega \text{ Min.} \\ \text{Insulation Resistance} & : 1000\text{M}\Omega \text{ Min.} \\ \text{Withstanding Voltage} & : 600\text{V AC/minute} \\ \text{Temperature Range} & : -25^{\circ}\text{C to} +85^{\circ}\text{C} \\ \end{array}$


Material

Insulator : Noryl (UL94V-1)

Diagram:







Dimensions

Part Number	Circuits/Ways	Dimension	
		A (mm)	B (mm)
2226A-02	2	5.28	2.54
2226A-03	3	7.82	5.08
2226A-04	4	10.36	7.62
2226A-05	5	12.9	10.16
2226A-06	6	15.44	12.7
2226A-08	8	20.52	17.78
2226A-10	10	25.6	22.86

Part Number	Circuits/Ways	Dimension	
		A (mm)	B (mm)
2226A-12	12	30.68	27.94
2226A-14	14	35.76	33.02
2226A-18	18	45.92	43.18
2226A-20	20	51	48.26
2226A-22	22	56.08	53.34
2226A-24	24	61.16	58.42

Notes:

A and B Dimension Tolerance:

2P to 10P : ±0.1 11P to 20P : ±0.2 21P to 30P : ±0.3



Crimp Housing



Part Number Table

Description	Part Number
Connector Housing, Receptacle, 2 Ways	2226A-02
Connector Housing, Receptacle, 3 Ways	2226A-03
Connector Housing, Receptacle, 4 Ways	2226A-04
Connector Housing, Receptacle, 5 Ways	2226A-05
Connector Housing, Receptacle, 6 Ways	2226A-06
Connector Housing, Receptacle, 8 Ways	2226A-08
Connector Housing, Receptacle, 10 Ways	2226A-10
Connector Housing, Receptacle, 12 Ways	2226A-12
Connector Housing, Receptacle, 14 Ways	2226A-14
Connector Housing, Receptacle, 18 Ways	2226A-18
Connector Housing, Receptacle, 20 Ways	2226A-20
Connector Housing, Receptacle, 22 Ways	2226A-22
Connector Housing, Receptacle, 24 Ways	2226A-24

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com www.farnell.com www.newark.com

