

Black Box Products

Datacom > Converters

PQ-7 Twinax to Laser-Quality ASCII Printer

Get complete 3812 emulation and autosharing!
PCA36A

Product Highlights

- Runs high-quality graphics and laser printers.
- Use with parallel-supported printers—parallel autosharing!

Further Details

The PQ-7 is the next step up from the PQ-6 Plus (RO) (PCA35A-R3). The PQ-7 provides complete emulation of 3812-1 and its autosharing feature enables your PC and your twinax host to share your ASCII laser printer. Just attach the host via the twinax port and the PC through the mini Centronics® parallel port. Print jobs are handled first come, first served. Printer cable is included.



Printers supported:

- IBM or compatible laser
- HP PCL® 4
- IBM PPDS
- Epson®

Product includes:

- (1) parallel printer cable
- (1) mini-Centronics to DB25 cable
- (1) DB9 twinax “V” cable

This product works with:

- Twinax Cable (EWN010) Questions? Contact Tech Support.

Emulation

IBM 4214, 5225, 5224, 5256, and 3812-1 (non IPDS)

Connectors	(1) DB9 twinax V-cable, (1) mini Centronics parallel, (1) 25-pin IBM PC parallel output to printer, (1) barrel for power F
Indicators	(4) LEDs: Power, Ready, Line Sync, PC Share
Power	115 VAC, 60 Hz, 15 watts (230-VAC, 50-Hz version on request)
Size	1.5"H x 6.3"W x 9.8"D (3.8 x 16 x 24.9 cm)
Weight	2.5 lb. (1.2 kg)

This product works with:

- Twinax Cable (EWN010) Questions? Contact Tech Support.

NOTE: Technical specification weight is the unit weight. It is not the packaged shipping weight. For shipping weight, please contact Black Box customer service at 1-800-316-7107.