

# Insulation Resistance Tester



## Specifications:



Basic Functions	Range		Best Accuracy
Insulation Resistance( $\Omega$ )	Test Voltage	100V/250V/500V/1000V	0%~10%
	100V	0.00M $\Omega$ ~100M $\Omega$	$\pm(3\%+5)$
		0.00M $\Omega$ ~99.9M $\Omega$	$\pm(3\%+5)$
	250V	100M $\Omega$ ~5.0G $\Omega$	$\pm(5\%+5)$
		0.00M $\Omega$ ~99.9M $\Omega$	$\pm(3\%+5)$
	500V	100M $\Omega$ ~5.0G $\Omega$	$\pm(5\%+5)$
		0.00M $\Omega$ ~99.9M $\Omega$	$\pm(3\%+5)$
	1000V	100M $\Omega$ ~5.0G $\Omega$	$\pm(5\%+5)$
		50V(R=50k $\Omega$ ) 1mA	0%~10%
	Load Current	100V(R=100k $\Omega$ ) 1mA	0%~10%
250V(R=250k $\Omega$ ) 1mA		0%~10%	
500V(R=500k $\Omega$ ) 1mA		0%~10%	
1000V(R=1M $\Omega$ ) 1mA		0%~10%	
Short Circuit Current			<2mA
AC Voltage (V)	30V to 750V		$\pm(2\%+3)$

## Special Functions

Basic Functions	Best Accuracy
Display Count	2,000
Auto Range	√
Low Battery Indication	√
LCD Backlight	√
Alarm Light Display	√
Alarm Buzzer	√
High Voltage Indication	√
Over Load Indication	√
Auto Discharge	√
Test Voltage Vice Display	√
10M $\Omega$ Internal Resistance Test	√

## General Characteristics

Power	1.5V Cells (LR6) × 6
LCD Size	70.6mm × 34mm
Product Color	Red and Grey
Product Net Weight	390 g

# Insulation Resistance Tester



Product Size	150mm × 100mm × 71mm
Standard Accessories	Cells, Probe, Alligator Clip, Test Lead, Gallus

## Part Number Table

Description	Part Number
Insulation Resistance Tester	72-9400A

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

