## XMLR010G2P05

Pressure sensors XMLR 10bar - G 1/4 - 24VDC - 2xPNP - M12



#### Main

| Range of product                        | OsiSense XM  |
|---|--|
| Product or component type               | Electronic pressure sensors  |
| Pressure switch type of operation       | Pressure switch with 2 switching outputs   |
| Device short name                       | XMLR   |
| Pressure sensor size                    | 10 bar<br>145 psi<br>1 MPa   |
| Maximum permissible accidental pressure | 40 bar<br>580 psi<br>4 MPa   |
| Destruction pressure                    | 40 bar<br>580 psi<br>4 MPa   |
| Controlled fluid                        | Refrigeration fluid (-2080 °C)<br>Hydraulic oil (-2080 °C)<br>Air (-2080 °C)<br>Fresh water (080 °C) |
| Fluid connection type                   | G 1/4 (female) conforming to DIN 3852-Y  |
| [Us] rated supply voltage               | 24 V DC SELV, voltage limits: 1733 V   |

## Complementary

| Complementary   |   |
|---|---|
| Current consumption                                     | <= 50 mA  |
| Electrical connection                                   | 4 pins M12 male connector   |
| Type of output signal                                   | Discrete  |
| Discrete output type                                    | Solid state PNP, 2 NO/NC programmable   |
| Maximum switching current                               | 250 mA  |
| Voltage drop  | <= 2 V  |
| Adjustable range of switching point on rising pressure  | 0.810 bar<br>11.6145 psi<br>0.081 MPa   |
| Adjustable range of switching point on falling pressure | 0.59.7 bar<br>7.25141 psi<br>0.050.97 MPa   |
| Minimum differential travel                             | 0.3 bar<br>4.35 psi<br>30 kPa   |
| Materials in contact with fluid                         | Ceramic<br>Fluorocarbon FKM (Viton)<br>316L stainless steel                               |
| Front material  | Polyester   |
| Housing material  | Polyacrylamide<br>316L stainless steel  |
| Operating position                                      | Any position, but disposals can falsified the measurement in case of upside down mounting |
| Protection type   | Overload protection Overvoltage protection Reverse polarity Short-circuit protection      |
| Response time on output                                 | <= 5 ms for discrete output   |
| Switching output time delay                             | 050 s in steps of 1 second  |
| Display type  | 4 digits 7 segments   |
| Local signalling  | 2 LEDs yellow for light ON when switch is actuated  |
|   |   |

| Display response time type               | Slow 600 ms  |
|--|--|
|  | Normal 200 ms  |
|  | Fast 50 ms   |
| Delay first up                           | <= 300 ms  |
| Overall accuracy                         | <= 1 % of the measuring range  |
| Measurement accuracy on switching output | <= 0.6 % of the measuring range  |
| Repeat accuracy                          | <= 0.2 % of the measuring range  |
| Drift of the sensitivity                 | +/- 0.03 % of measuring range/°C   |
| Drift of the zero point                  | +/- 0.1 % of measuring range/°C  |
| Display accuracy                         | <= 1 % of the measuring range  |
| Mechanical durability                    | >= 10000000 cycles   |
| Depth                                    | 42 mm  |
| Height                                   | 93 mm  |
| Width                                    | 41 mm  |
| Product weight                           | 0.19 kg  |
| [Uimp] rated impulse withstand voltage   | 0.5 kV DC  |
| Electromagnetic compatibility            | Electrostatic discharge immunity test - test level 8 kV air, 4 kV contact conforming                     |
|  | to EN/IEC 61000-4-2  |
|  | Electrical fast transient/burst immunity test - test level 2 kV conforming to EN/IEC 61000-4-4           |
|  | Surge immunity test - test level 1 kV conforming to EN/IEC 61000-4-5                                     |
|  | Immunity to conducted RF disturbances - test level 10 V (0.1580 MHz) con-                                |
|  | forming to EN/IEC 61000-4-6  |
|  | Susceptibility to electromagnetic fields - test level 10 V/m (802000 MHz) conforming to EN/IEC 61000-4-3 |

## Environment

| LITVITOTITICITE                       |  |
|---------------------------------------|--|
| Marking                               | CE   |
| Product certifications                | CULus<br>EAC   |
| Standards                             | UL 61010-1<br>EN/IEC 61326-2-3                                     |
| Ambient air temperature for operation | -2080 °C   |
| Ambient air temperature for storage   | -4080 °C   |
| IP degree of protection               | IP67 conforming to EN/IEC 60529<br>IP65 conforming to EN/IEC 60529 |
| Vibration resistance                  | 20 gn (f = 102000 Hz) conforming to EN/IEC 60068-2-6               |
| Shock resistance                      | 50 gn conforming to EN/IEC 60068-2-27                              |
|                                       |  |

## Offer Sustainability


| Sustainable offer status | Not Green Premium product   |
|--------------------------|---|
| RoHS (date code: YYWW)   | Compliant - since 1351 - Schneider Electric declaration of conformity |
| REACh                    | Reference not containing SVHC above the threshold                     |



# Product data sheet Dimensions Drawings

# XMLR010G2P05

## **Dimensions**




(1) Fluid entry: G 1/4 A female

## Product data sheet Connections and Schema

# XMLR010G2P05


## Connections and Schema

## **Connector Wiring**



## Switching Output Description. Hysteresis Mode

The hysteresis switching mode is typically used for the "pumping and/or emptying applications".




X: Time Y: Pressure (1) Output

NP: Nominal Pressure

SP: Set point (adjustable from 8 % to 100 % NP) rP: Reset point (adjustable from 5 % to 97 % NP)

## Switching Output Description. Window Mode

The window switching mode is typically used for the "pressure regulation applications"



X: Time Y: Pressure (1) Output


NP: Nominal pressure

FH : High switching point (adjustable from 8 % to 100 % NP) FL : Low switching point (adjustable from 5 % to 97 % NP)

## Switching Output Description. Time Delay

The Time Delay is typically used to filter out the fast pressure transients.

The output only switches after a time "dS" and "dr" adjustable from 0 to 50 seconds.



X: Time
Y: Pressure
(1) Output
SP: Set point
rP: Reset point
dS: Time delay on the set point
dr: Time delay on the reset point