

7/16 F/F In/Out RF Coaxial Surge Protector 100MHz - 512MHz DC Block 750W IP67 20kA Filter BiDirect Bracket Toward Body

RF Surge Protectors Technical Data Sheet

LCSP1037

Features

- · Surge current of 20kA
- Max Power 750W
- Frequency range from 100 MHz to 512 MHz VHF Band
- 7/16 DIN Female to 7/16 DIN Female connectors
- VSWR 1.1:1

- · Waterproof IP67 rated
- DC Block
- Multi-strike capability
- · CE & RoHS compliant
- Bi-Directional

Applications

• Emergency response systems

· Public safety systems

Description

RF surge protector (also known as lightning arrester) LCSP1037 from L-COM utilizing a patented filter surge protection technology acts as a high-band filter shunting surge energy to ground to protect critical hardware while maintaining the RF performance. This RF surge protector component is manufactured in a coaxial in-line design with wide operating frequency range. All L-COM RF surge protector products are available in stock with same day shipping.

Electrical Specifications

Surge Protector Type DC Handling

Surge Filter DC Block

| Description | Minimum | Typical | Maximum | Units |
|------------------------------|---------|---------|---------|-------|
| Frequency Range | 100 | | 512 | MHz |
| Impedance | | 50 | | Ohms |
| VSWR | | | 1.1:1 | |
| Return Loss | | | 26 | dB |
| Insertion Loss | | | 0.1 | dB |
| Input Power, CW | | | 750 | Watts |
| Surge Current | | | 20 | kAmps |
| IEC 61000-4-5 8/20μs WAVEFOR | M | | | |
| Throughput Energy | | | 0.5 | μJ |
| FOR 3kA, 8/20µs WAVEFORM | | | | |

Mechanical Specifications

Configuration

Input Connector
Output Connector

7/16 DIN Female 7/16 DIN Female

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 7/16 F/F In/Out RF Coaxial Surge Protector 100MHz - 512MHz DC Block 750W IP67 20kA Filter BiDirect Bracket Toward Body LCSP1037



7/16 F/F In/Out RF Coaxial Surge Protector 100MHz - 512MHz DC Block 750W IP67 20kA Filter BiDirect Bracket Toward Body



RF Surge Protectors Technical Data Sheet

LCSP1037

Environmental Specifications

Temperature

Operating Range Ingress Protection (IP) Rating -50 to 85 deg C

P 67

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Our portfolio includes cable assemblies, connectors, adapters and custom products, as well as their wireless product line which includes antennas, RF amplifiers, coaxial lightning and surge protectors, and NEMA rated enclosures.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 7/16 F/F In/Out RF Coaxial Surge Protector 100MHz - 512MHz DC Block 750W IP67 20kA Filter BiDirect Bracket Toward Body LCSP1037

URL:

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume any liability arising out of the use of any part or documentation.

L-com, Inc. • 50 High St., West Mill, 3rd Floor, Suite #30 North Andover, MA 01845 © 2018 L-com, Inc. All Right Reserved

Phone: 1-800-343-1455 • sales@L-com.com

LCSP1037 CAD Drawing
7/16 F/F In/Out RF Coaxial Surge Protector 100MHz - 512MHz DC Block 750W IP67 20kA Filter BiDirect Bracket Toward Body

