## Inductor



## RoHS Compliant



## **Specifications:**

Inductance : 100µH Inductance Tolerance : ± 20% DC Resistance Max : 0.2Ω DC Current Rating : 2A : SMD Inductor Case Style No. of Pins Lead Spacing : 12.7mm External Depth : 7.62mm External Length / Height : 18.54mm External Width : 15.24mm Series : MCB

### **Electrical Characteristics (at 25°C)**

100kHz 0.25V	L	100μH ±20%
at 25°C	DCR	207mΩ (Max.)
100KHz 0.1V Irms = 1.7A	L at Irms	ΔT40°C (Maximum)

Operating temperature: -55°C to +130°C **Note:** Irms **Temperature Rise 40°C** 

#### **Material List**

No.	Item	Material Description
1	Core	N5D DR9.7 × 5.8 N5D RI12.7 × 5.7 × 10.8
2	Wire	Ø0.37mm × 1P 2UEWF 155°C
3	Solder (Lead Free)	Sn99.3%/Cu0.7%
4	Glue	TH320D / TH320-3
5	Base	DR13-RT-A DAP


Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



## Inductor




## **Schematic Diagram**




#### Note:

- 1. Wire Ø0.37mm × 1P 2UEWF 155°C
- 2. 38.5TS (Reference)

### **Electric Characteristics**






Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



# Inductor



### **Configurations and Dimensions**



Dimensions: Millimetres

Α	18.54mm	(Maximum)
В	15.24mm	(Maximum)
С	7.62mm	(Maximum)
D	12.7 ±0.3mm	-
E	12.7mm	(Reference)
F	2.54mm	(Reference)
G	2.54mm	(Reference)

#### **Part Number Table**

Description	Part Number
Inductor, 100µH, 20%, SMD	MCBFS7330-101MU

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

