## **DATASHEET - NZM2-XSVS**



Socket 3p, 250A

Part no. NZM2-XSVS Catalog No. 266699

EL-Nummer (Norway) 0004359020



### **Delivery program**

Delivery program			
Accessories			
Plug-in socket for basic unit			
IEC			
Plug-in units			
NZM2			
Plug base for use with basic units NZMSVE of the respective size			
3 pole			
Screw connection			

### **Technical data**

#### General

General		
Standards		IEC/EN 60947
Protection against direct contact		Finger and back-of-hand proof to VDE 0106 part 100
Climatic proofing		Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Ambient temperature		
Ambient temperature, storage	°C	- 40 - + 70
Operation	°C	-25 - +70
Mechanical shock resistance (10 ms half-sinusoidal shock) according to IEC 60068-2-27	g	20 (half-sinusoidal shock 20 ms)
Safe isolation to EN 61140		
Between auxiliary contacts and main contacts	V AC	500
between the auxiliary contacts	V AC	300
Mounting position		Vertical and 90° right/left
Direction of incoming supply		as required
Degree of protection		
Device		IP2X (in the area of the plug-in area)

## **Design verification as per IEC/EN 61439**

and the second section of the second			
Technical data for design verification			
Equipment heat dissipation, current-dependent	$P_{vid}$	W	18.75
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			

10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must lobserved.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must lobserved.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Chassis part power circuit breaker (EC002043)						
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Chassis part circuit breaker (ecl@ss10.0.1-27-37-04-22 [ACN955011])						
Rated current In	А	230				
Number of poles		3				
Version as busbar adapter		No				
Version as built-in device		Yes				
Type of electrical connection of main circuit		Screw connection				

# **Dimensions**

