Vishay Sfernice



Power Resistors, for Mounting onto a Heatsink Thick Film Technology



Manufactured in cermet thick film technology, these power resistors exhibit remarkable characteristics and the series includes 4 types ranging from 5 W to 50 W

Designed to be mounted onto a heatsink, the resistors can bear high short time overloads and 3 types of terminations are available.


The resistors are non inductive and are particularly suitable for high frequency operation and cut-out circuits.


FEATURES

- 5 Watt to 50 W
- High power rating
- · High overload capabilities up to 2500 V RMS
- Wide resistance range from 0R24 to 1 $\mbox{M}\Omega$
- High thermal capacity up to 0.8 °C/W
- · Easy mounting
- Reduced size and weight
- High insulation: $10^6\,\text{M}\Omega$

Pb RoHS

DIMENSIONS in millimeters





RCH...V



• General Tolerance: ± 0.3 mm

DIMENSIONS						
MODEL	RCH 5	RCH 10	RCH 25	RCH 50		
L	16.6	19	28	47.8		
w	9	11	14	15.5		
Н	16.4	20.6	27.5	29.4		
P Leads pitch	10.2	12.7	18.3	30.5		
F Connections pitch	11.3	14.3	18.3	39.7		
Т	12.5	15.9	19.8	21.4		
S	5.3	5	7.7	8		
ØD	2.4	2.4	3.2	3.2		
V Leads	M2	M2	M3	M3		
Weight (g)	4	5	7	12		





Power Resistors, for Mounting onto a Heatsink Thick Film Technology

Vishay Sfernice

MECHANICAL SPECIFICATIONS

Mechanical Protection Insulated Case

Substrate Alumina
Resistive Element Cermet

Connections Tinned copper alloy

ENVIRONMENTAL SPECIFICATIONS

Temperature Range - 55 °C to + 125 °C

Climatic Category 55/125/56

ELECTRICAL SPECIFICATIONS				
Resistance Range	0.24 Ω to 1 M Ω E24 series			
Standard Resistance Tolerances	± 1 %, ± 2 %, ± 5 %, ± 10 %			
Power Rating				
Chassis Mounted	5 W to 50 W			
Unmounted	2 W to 5.5 W			
Temperature Coefficient	± 150 ppm/°C (R > 1 Ω)			
Insulation Resistance	$10^6\mathrm{M}\Omega$			
Total Inductance	≤ 0.1 µH			

PERFORMANCE					
TESTS	CONDITIONS	TYPICAL DRIFTS			
Momentary Overload	NF EN 140 000 CEI 115_1 2 Pr/5 s Us < 2 UL	< ± (0.25 % + 0.05 Ω)			
Rapid Temperature Change	NF EN 140 000 125°C CEI 68215 Test Na 5 cycles - 55 °C to + 125 °C	< ± (0.25 % + 0.05 Ω)			
Load Life	NF EN 140 000 CEI 115_1 1000 h Pr at + 25°C	< ± (0.5 % + 0.05 Ω)			
Humidity (Steady State)	56 days R.H. 95 % MIL STD 202 Method 103 B and C	< ± (0.5 % + 0.05 Ω)			

RESISTANCE VALUE IN RELATION TO TOLERANCE AND TCR					
Resistance Value	< 1 Ω > 1 Ω				
Standard Tolerances	± 5 % ± 10 %				
Standard TCR	± 250 ppm/°C	± 150 ppm/°C			
Tolerance on Request	± 1 % to ± 2 %				

SPECIAL FEATURES					
MODEL	RCH 5	RCH 10	RCH 25	RCH 50	
Power Rating-Chassis Mounted	5 W	10 W	25 W	50 W	
Power Rating-Unmounted	2 W	2.5 W	4 W	5.5 W	
Thermal Resistance RTH (j-c)	4.8 °C/W	3.2 °C/W	1.4 °C/W	0.8 °C/W	
Limiting Element Voltage (VRMS)	160 V	250 V	550 V	1285 V	
Max. Overload Voltage (VRMs)	320 V	500 V	1100 V	2500 V	
Dielectric Strength (VRMs) 50 Hz, 1 minute MIL STD 202 Method 301 10 mA Max	2000 V	2000 V	3500 V	3500 V	
Critical Resistance	5120 Ω	6250 Ω	12 100 Ω	33 024 Ω	



Vishay Sfernice

Power Resistors, for Mounting onto a Heatsink Thick Film Technology



RECOMMENDATIONS FOR MOUNTING ONTO A HEATSINK

Surfaces in contact must be carefully cleaned.

The heatsink must have an acceptable flatness: from 0.05 mm to 0.1 mm/100 mm.

Roughness of the heatsink must be around 6.3 μm. In order to improve thermal conductivity, surfaces in contact (alumina, heatsink) are coated with a silicone grease (type SI 340 from Rhône-Poulenc or Dow 340 from Dow Corning).

The fastening of the resistor to the heatsink is under pressure control of two screws (not supplied).

Tightening Torque on heatsink	RCH 5	RCH 10	RCH 25	RCH 50
	0.5 Nm	0.6 Nm	0.7 Nm	1 Nm

In order to improve the dissipation, either forced-air cooling or liquid cooling may be used.

A low thermal radiation of the case allows several resistors to be mounted onto the same heatsink.

Do not forget to respect an insulation value between two resistors (dielectric strength in dry air 1 kV/mm).

In any case the hot spot temperature, measured locally on the case must not exceed 125 °C.

Tests should be performed by the user.

CHOICE OF HEATSINK

The user must choose the heatsink according to working conditions of the component (power, room temperature). Maximum working temperature must not exceed 125 °C. The dissipated power is simply calculated by the following ratio:

$$P = \frac{\Delta T}{[RT_H(j-c) + RT_H(c-a)]}$$

P: Expressed in W

 ΔT : Difference between maximum working temperature and room temperature.

RTH: (j-c): Thermal resistance value measured between resistance layer and outer side of the resistor.

It is the thermal resistance of the component (See Special Features table).

RTH: (c-a): Thermal resistance value measured between outer side of the resistor and room temperature.

It is the thermal resistance of the heatsink depending on the heatsink itself (type, shape) and the quality of the fastening device.

Example:

RTH: (c-a) for RCH 25 power rating 20 W at ambient temperature + 50 °C.

$$\Delta T \le 125~^{\circ}C$$
 - 50 $^{\circ}C \le 75~^{\circ}C$

RTH (j-c) = 1.4 °C/W (Special Features)

R_{TH} (j-c) + R_{TH} (c-a) =
$$\frac{\Delta T}{P} = \frac{75}{20} = 3.75$$
 °C/W

R_{TH} (c-a) ≤ 3.75 °C/W - 1.4 °C/W ≤ 2.35 °C/W




Power Resistors, for Mounting onto a Heatsink Thick Film Technology

Vishay Sfernice

OVERLOADS

The applied voltage must always be lower than the maximum overload voltage as shown in the special features table. The values indicated on the graph below are applicable to resistors in air or mounted onto a heatsink.


ENERGY CURVE



POWER RATING CHART

For resistors mounted onto heatsink and thermal resistance of 1 °C/W.

To improve the thermal conductivity, surfaces in contact should be coated with a silicone grease.




Packaging Bag of 25 units

MARKING

Model, Style, Resistance Value (in Ω), Tolerance (in %), Manufacturing Date, VISHAY trade mark.

ORDERING INFORMATION							
RCH	10	3K3	5 %	S	xxx	BA25	e3
MODEL	SIZE	OHMIC VALUE	TOLERANCE	CONNECTIONS	CUSTOM DESIGN	PACK	LEAD (Pb)-free
			± 1 % ± 2 % ± 5 % ± 10 %	S: Flat with hole R: Round lead V: M2 screw	Optional		



Legal Disclaimer Notice



Vishay

Notice

Specifications of the products displayed herein are subject to change without notice. Vishay Intertechnology, Inc., or anyone on its behalf, assumes no responsibility or liability for any errors or inaccuracies.

Information contained herein is intended to provide a product description only. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document. Except as provided in Vishay's terms and conditions of sale for such products, Vishay assumes no liability whatsoever, and disclaims any express or implied warranty, relating to sale and/or use of Vishay products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright, or other intellectual property right.

The products shown herein are not designed for use in medical, life-saving, or life-sustaining applications. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Vishay for any damages resulting from such improper use or sale.

www.vishay.com Revision: 08-Apr-05