

PRODUCT-DETAILS

F202 A-40/0.03 AP-R F202 A-40/0.03 AP-R Residual Current Circuit Breaker 2P A type 30 mA



General Information		
Extended Product Type	F202 A-40/0.03 AP-R	
Product ID	2CSF202401R140	
EAN	801254278520	
Catalog Description	F202 A-40/0.03 AP-R Residual Current Circuit Breaker 2P A type 30 r	
Long Description	The RCCBs F200 series assures protection to people and installations against fault currer to earth. A large offer for standard instantaneous and selective AC and A types is complete with some configurations for special applications. This product provides the be compromise between safety and continuity in the service, thanks to the resistance unwanted tripping	
Circular Value Circular Design Principles	Design for Closing Resource Loops - Standard EN45555 - 52.5 %	
Recyclability Rate		
Sustainable Material Content	0 %	
End of Life Instructions	9AKK108468A4361	
Ego Trongnoronov		
Eco Transparency		
Environmental Product Declaration - EPD	9AKK108467A3700	

F202 A-40/0.03 AP-R 2

Technical	
Standards	IEC/EN 61008 UL 1053
Type of Residual Current	A type
Rated Voltage (U _r)	230 V
Rated Operational Voltage	230 V
Rated Insulation Voltage (U_i)	500 V
Rated Impulse Withstand Voltage (U _{imp})	4 kV
Input Voltage Type	AC
Rated Current (I _n)	40 A
Rated Residual Current	30 mA
Rated Conditional Short- Circuit Current (I _{nc})	10 kA
Rated Service Short- Circuit Breaking Capacity (I _{cs})	1 kA
Maximum Surge Current	3 kA
Leakage Current Type	A
Rated Frequency (f)	50 60 Hz
Power Loss	at Rated Operating Conditions per Pole 2.4 W
Power Supply Connection	Arbitrary
Electrical Endurance	10000 cycle
Number of Poles	2
Operating Characteristic	Instantaneous (APR High Immunity)
Mounting Type	DIN-Rail
Options Provided	None
Accessories Available	Yes
Connecting Capacity	Busbar 10 mm² Rigid 25 25 mm² Flexible 25 25 mm²
Rated Cross-Section	4 - Multi-Wired 025 mm² 1 - Solid-Core 2525 mm²
Fin size and a state	
Environmental	
Ambient Temperature	-2555 °C
Ambient Air Temperature	Operation -2555 °C
Degree of Protection	IP2X
Pollution Degree	2
Resistance to Vibrations acc. to IEC 60068-2-6	0.1 mm or 1 g - 20 cycles at 51505 Hz
Resistance to Shock acc. to IEC 60068-2-27	25g 2 shocks 13 ms
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
RoHS Information	9AKK106713A5602
REACH Declaration	9AKK108467A9482
Environmental Information	Refer to RoHS
SCIP	18f132b0-8f03-4611-9c59-dba03cc369bf Italy (IT)
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

F202 A-40/0.03 AP-R 3

Maximum Operating Voltage UL/CSA	277 V AC
Short-Circuit Current Rating (SCCR)	30 mA
iding (coort)	
Dimensions	
Width in Number of Modular Spacings	
Product Net Width	0.035 n
Product Net Height	0.085 n
Product Net Depth / Length	0.069 r
Product Net Weight	0.200 kg
Built-In Depth (t ₂)	69 mn
Ordering	
Minimum Order Quantity	1 piec
Package Level 1 Units	box 1 piece
Package Level 1 Gross Weight	0.235 kg
Customs Tariff Number	8536303
E-Number (Finland)	325966
E-Number (Sweden)	216017
Country of Origin	Italy (IT
Certificates and Declarations Declaration of Conformity	9AKK106713A5602
- CE	
Popular Downloads	
Data Sheet, Technical	
Data Sheet, Technical nformation	9AKK107991A832: 9AKK107991A612
Data Sheet, Technical nformation	9AKK107991A832:
Data Sheet, Technical Information Instructions and Manuals	9AKK107991A832
Data Sheet, Technical Information Instructions and Manuals Classifications ETIM 8	9AKK107991A832 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCE
Classifications ETIM 8 ETIM 9	9AKK107991A832: 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCB
Classifications ETIM 8 ETIM 9 EPLAN Catalog Tree	9AKK107991A832 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCE EC000003 - Residual current circuit breaker (RCCE EC000003 - Residual current circuit breaker (RCCE Electrical engineering / Protection devices / Ground fault current circuit breaker
Data Sheet, Technical Information Instructions and Manuals Classifications ETIM 8 ETIM 9 EPLAN Catalog Tree EPLAN Function Definition	9AKK107991A832 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCE EC000003 - Residual current circuit breaker (RCCE EC000003 - Residual current circuit breaker (RCCE Electrical engineering / Protection devices / Ground fault current circuit breaker Ground fault current circuit-breaker / Ground fault current circuit breakers, 4 connection points / Ground fault current circuit breaker, two-pole 1/2 2/1 3/4 4/
Classifications ETIM 8 ETIM 9 EPLAN Catalog Tree EPLAN Function Definition WEEE Category	9AKK107991A832 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCE EC000003 - Residual current circuit breaker (RCCE Electrical engineering / Protection devices / Ground fault current circuit breaker Ground fault current circuit-breaker / Ground fault current circuit breakers, 4 connection points / Ground fault current circuit breakers, 4 5. Small Equipment (No External Dimension More Than 50 cm
Classifications ETIM 8 ETIM 9 EPLAN Catalog Tree EPLAN Function Definition WEEE Category WEEE B2C / B2B	9AKK107991A832 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCE EC000003 - Residual current circuit breaker (RCCE Electrical engineering / Protection devices / Ground fault current circuit breaker Ground fault current circuit-breaker / Ground fault current circuit breakers, 4 connection points / Ground fault current circuit breakers, 4 5. Small Equipment (No External Dimension More Than 50 cm Business To Consume
Data Sheet, Technical Information Instructions and Manuals Classifications ETIM 8 ETIM 9 EPLAN Catalog Tree EPLAN Function Definition WEEE Category WEEE B2C / B2B CN8	9AKK107991A832 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCE EC000003 - Residual current circuit breaker (RCCE Electrical engineering / Protection devices / Ground fault current circuit breaker Ground fault current circuit-breaker / Ground fault current circuit breakers, a connection points / Ground fault current circuit breakers, two-pole 1/2 2/1 3/4 4/ 5. Small Equipment (No External Dimension More Than 50 cm Business To Consume
Data Sheet, Technical Information Instructions and Manuals Classifications ETIM 8 ETIM 9 EPLAN Catalog Tree EPLAN Function Definition WEEE Category WEEE B2C / B2B CN8 UNSPSC	9AKK107991A832 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCE EC000003 - Residual current circuit breaker (RCCE Electrical engineering / Protection devices / Ground fault current circuit breaker Ground fault current circuit-breaker / Ground fault current circuit breakers, connection points / Ground fault current circuit breakers, two-pole 1/2 2/1 3/4 4/ 5. Small Equipment (No External Dimension More Than 50 cm Business To Consume 8536303
Data Sheet, Technical Information Instructions and Manuals Classifications ETIM 8 ETIM 9 EPLAN Catalog Tree EPLAN Function Definition WEEE Category WEEE B2C / B2B CN8 UNSPSC eClass	9AKK107991A832 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCE EC000003 - Residual current circuit breaker (RCCE Electrical engineering / Protection devices / Ground fault current circuit breaker Ground fault current circuit-breaker / Ground fault current circuit breakers, connection points / Ground fault current circuit breaker, two-pole 1/2 2/1 3/4 4/ 5. Small Equipment (No External Dimension More Than 50 cm Business To Consume 8536303 3912160 V11.0: 2714220
Popular Downloads Data Sheet, Technical Information Instructions and Manuals Classifications ETIM 8 ETIM 9 EPLAN Catalog Tree EPLAN Function Definition WEEE Category WEEE B2C / B2B CN8 UNSPSC eClass IDEA Granular Category © 2023 ABB. All rights reserved.	9AKK107991A832 9AKK107991A612 EC000003 - Residual current circuit breaker (RCCI EC000003 - Residual current circuit breaker (RCCI EC000003 - Residual current circuit breaker (RCCI Electrical engineering / Protection devices / Ground fault current circuit breaker Ground fault current circuit-breaker / Ground fault current circuit breakers, connection points / Ground fault current circuit breakers, tonnection points / Ground fault current circuit breaker, two-pole 1/2 2/1 3/4 4. 5. Small Equipment (No External Dimension More Than 50 cm Business To Consum- 8536303

Code (IGCC)

Object Classification Code	

Accessories				
ldentifier	Description	Туре	Quantity	Unit Of Measure
2CDS200912R0001	S2C-H6R Auxiliary Contact	S2C-H6R	2	piece
2CDS200922R0001	S2C-S/H6R Signal / Auxiliary Contact	S2C-S/H6R	2	piece
2CDS200946R0001	S2C-H6-11R Auxiliary Contact	S2C-H6-11R	1	piece
2CDS200946R0003	S2C-H6-02R Auxiliary Contact	S2C-H6-02R	1	piece
2CDS200946R0002	S2C-H6-20R Auxiliary Contact	S2C-H6-20R	1	piece
2CSS200933R0011	F2C-A1 Shunt trip	F2C-A1	1	piece
2CSS200933R0012	F2C-A2 Shunt trip	F2C-A2	1	piece
2CSS200911R0005	S2C-UA 230 AC Undervoltage release	S2C-UA 230 AC	1	piece
2CSS200911R0007	S2C-UA 24 DC Undervoltage release \$	1	piece	
2CSS200911R0002	S2C-UA 24 AC Undervoltage release S2C-UA 24 AC		1	piece
2CSS200911R0008	S2C-UA 48 DC Undervoltage release \$	S2C-UA 48 DC	1	piece
2CSS200911R0004	S2C-UA 110 AC Undervoltage release	S2C-UA 110 AC	1	piece
2CSS200911R0006	S2C-UA 400 AC Undervoltage release	S2C-UA 400 AC	1	piece
2CSS200911R0001	S2C-UA 12 DC Undervoltage release S	1	piece	
2CSS200911R0010	S2C-UA 230 DC Undervoltage release	S2C-UA 230 DC	1	piece
2CSS200911R0009	S2C-UA 110 DC Undervoltage release	S2C-UA 110 DC	1	piece
2CSS200911R0003	S2C-UA 48 AC Undervoltage release S	S2C-UA 48 AC	1	piece
2CSS200910R0005	S2C-OVP1 Overvoltage release	S2C-OVP1	1	piece
2CSS200993R0005	S2C-OVP2 Overvoltage release	S2C-OVP2	1	piece
2CSF200997R0013	F2C-CM Motor operating device	F2C-CM	1	piece
2CSF200996R0013	F2C-ARI Auto-reclosing unit	F2C-ARI	1	piece
2CSF200995R0013	F2C-ARI30 Auto-reclosing unit	F2C-ARI30	1	piece
2CSF200992R0005	F2C-ARH Auto-reclosing unit	F2C-ARH	1	piece
2CSF200991R0005	F2C-ARH -T Auto-reclosing unit with autotest	F2C-ARH -T	1	piece

Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Modular\ DIN\ Rail\ Products \rightarrow Residual\ Current\ Devices\ RCDs \rightarrow Residual\ Current\ Devices\ RCDs$





