

PRODUCT-DETAILS

F202 A-63/0.03 110V F202 A-63/0.03 110V Residual Current Circuit Breaker 2P A type 30 mA



| General Information | | |
|--|---|--|
| Extended Product Type | F202 A-63/0.03 110V | |
| Product ID | 2CSF202199R1630 | |
| EAN | 8012542343134 | |
| Catalog Description | F202 A-63/0.03 110V Residual Current Circuit Breaker 2P A type 30 mA | |
| Long Description | The RCCBs F200 series assures protection against the effects of sinusoidal alternating and direct pulsating earth fault currents, protection, against indirects contacts and additional protection against direct (with sensitivity = 30 mA) contacts. Applications: residential, commercial, industrial. This particular serias has the minimum operating voltage of test buttom 0f 110V and it is suitable for application at 230V. | |
| Circular Value | | |
| Circular Design Principles Recyclability Rate | Design for Closing Resource Loops - Standard EN45555 - 52,5 % | |
| Sustainable Material Content | 0 % | |
| End of Life Instructions | 9AKK108468A4361 | |
| | | |
| Eco Transparency | | |
| Environmental Product Declaration - EPD | 9AKK108467A3700 | |

| Technical | | |
|---|---|--|
| Standards | IEC 61008 UL 1053 | |
| Type of Residual Current | A type | |
| Rated Voltage (U _r) | 230 V | |
| Rated Operational Voltage | 230 V | |
| Rated Insulation Voltage (U _i) | 500 V | |
| Test Voltage (Ut) | 110 V | |
| Rated Impulse Withstand Voltage (U _{imp}) | 4 KV | |
| Input Voltage Type | AC | |
| Rated Current (I _n) | 63 A | |
| Rated Residual Current | 30 mA | |
| Rated Conditional Short- Circuit Current (I _{nc}) | 10 kA | |
| Rated Service Short- Circuit Breaking Capacity (I _{cs}) | 1 kA | |
| Leakage Current Type | A | |
| Rated Frequency (f) | 50 60 Hz | |
| Power Loss | at Rated Operating Conditions per Pole 3.2 W | |
| Power Supply Connection | Arbitrary | |
| Electrical Endurance | 10000 cycle | |
| Number of Poles | 2 | |
| Operating Characteristic | Instantaneous | |
| Mounting Type | DIN-Rai | |
| Options Provided | None, Suitable for 110V applications | |
| Accessories Available | Yes | |
| Connecting Capacity | Busbar 10 mm Rigid 25 25 mm Flexible 25 25 mm | |
| Rated Cross-Section | 4 - Multi-Wired 025 mm 1 - Solid-Core 2525 mm | |
| | 1 * Solid-Core 2325 min | |
| Environmental | | |
| Ambient Temperature | -2555 °C | |
| Ambient Air Temperature | Operation -2555 °C | |
| Degree of Protection | IP2X | |
| Pollution Degree | 2 | |

| Technical UL/CSA | | |
|--|---------|--|
| Maximum Operating Voltage UL/CSA | 277 V A | |
| Short-Circuit Current Rating (SCCR) | 30 mA | |

| Dimensions | |
|--|----------|
| Width in Number of Modular Spacings | 2 |
| Product Net Width | 0.035 m |
| Product Net Height | 0.085 m |
| Product Net Depth / Length | 0.069 m |
| Product Net Weight | 0.200 kg |
| Built-In Depth (t ₂) | 69 mm |

| Ordering | |
|---------------------------------|-------------|
| Minimum Order Quantity | 1 piece |
| Package Level 1 Units | box 1 piece |
| Package Level 1 Gross Weight | 0.235 kg |
| Customs Tariff Number | 85363030 |
| E-Number (Sweden) | 2160064 |
| Country of Origin | Italy (IT) |

Certificates and Declarations

| Declaration of Conformity | 9AKK106713A5602 |
|---------------------------|-----------------|
| - CE | |

| Popular Downloads | | |
|--------------------------------------|-----------------|--|
| Data Sheet, Technical Information | 9AKK107991A8329 | |
| Instructions and Manuals | 9AKK107991A6127 | |
| EPLAN Macro | 9AKK106930A1238 | |

| Classifications | |
|------------------------------|--|
| ETIM 8 | EC000003 - Residual current circuit breaker (RCCB) |
| ETIM 9 | EC000003 - Residual current circuit breaker (RCCB) |
| EPLAN Catalog Tree | Electrical engineering / Protection devices / Ground fault current circuit breaker |
| EPLAN Function Definition | Ground fault current circuit-breaker / Ground fault current circuit breakers, 4 connection points / Ground fault current circuit breaker, two-pole 1/2 2/1 3/4 4/3 |
| WEEE Category | 5. Small Equipment (No External Dimension More Than 50 cm) |
| WEEE B2C / B2B | Business To Consumer |
| CN8 | 85363030 |
| UNSPSC | 39121601 |
| eClass | V11.0 : 27142201 |
| IDEA Granular Category | 4875 >> Residual current circuit breaker (RCCB) |

© 2023 ABB. All rights reserved.

2023/08/08

Subject to change without notice

Code (IGCC)

Object Classification Code

| | | | | Accessories |
|-------------------|----------|--|--|-----------------|
| Unit C Measure | Quantity | Туре | Description | Identifier |
| piec | 2 | S2C-H6R | S2C-H6R Auxiliary Contact | 2CDS200912R0001 |
| piece | 2 | S2C-S/H6R | S2C-S/H6R Signal / Auxiliary Contact | 2CDS200922R0001 |
| piec | 1 | S2C-H6-11R | S2C-H6-11R Auxiliary Contact | 2CDS200946R0001 |
| piec | 1 | S2C-H6-02R | S2C-H6-02R Auxiliary Contact | 2CDS200946R0003 |
| piec | 1 | S2C-H6-20R | S2C-H6-20R Auxiliary Contact | 2CDS200946R0002 |
| piec | 1 | F2C-A1 | F2C-A1 Shunt trip | 2CSS200933R0011 |
| piec | 1 | F2C-A2 | F2C-A2 Shunt trip | 2CSS200933R0012 |
| piec | 1 | S2C-UA 230 AC | S2C-UA 230 AC Undervoltage release | 2CSS200911R0005 |
| piec | 1 | 2CSS200911R0007 S2C-UA 24 DC Undervoltage release S2C-UA 24 DC | | |
| piec | 1 | 2CSS200911R0002 S2C-UA 24 AC Undervoltage release S2C-UA 24 AC | | |
| piec | 1 | CSS200911R0008 S2C-UA 48 DC Undervoltage release S2C-UA 48 DC | | |
| piece | 1 | S2C-UA 110 AC | S2C-UA 110 AC Undervoltage release | 2CSS200911R0004 |
| piece | 1 | S2C-UA 400 AC | S2C-UA 400 AC Undervoltage release | 2CSS200911R0006 |
| piec | 1 | S2C-UA 12 DC | S2C-UA 12 DC Undervoltage release S | 2CSS200911R0001 |
| piec | 1 | S2C-UA 230 DC | S2C-UA 230 DC Undervoltage release | 2CSS200911R0010 |
| piece | 1 | S2C-UA 110 DC | S2C-UA 110 DC Undervoltage release | 2CSS200911R0009 |
| piec | 1 | 62C-UA 48 AC | S2C-UA 48 AC Undervoltage release S | 2CSS200911R0003 |
| piec | 1 | S2C-OVP1 | S2C-OVP1 Overvoltage release | 2CSS200910R0005 |
| piec | 1 | S2C-OVP2 | S2C-OVP2 Overvoltage release | 2CSS200993R0005 |
| piec | 1 | F2C-CM | F2C-CM Motor operating device | 2CSF200997R0013 |
| piec | 1 | F2C-ARI | F2C-ARI Auto-reclosing unit | 2CSF200996R0013 |
| piec | 1 | F2C-ARI30 | F2C-ARI30 Auto-reclosing unit | 2CSF200995R0013 |
| piec | 1 | F2C-ARH | F2C-ARH Auto-reclosing unit | 2CSF200992R0005 |
| piec | 1 | F2C-ARH -T | F2C-ARH -T Auto-reclosing unit with autotest | 2CSF200991R0005 |

Categories

 $\mathsf{Low}\ \mathsf{Voltage}\ \mathsf{Products}\ \mathsf{and}\ \mathsf{Systems}\ \rightarrow\ \mathsf{Modular}\ \mathsf{DIN}\ \mathsf{Rail}\ \mathsf{Products}\ \rightarrow\ \mathsf{Residual}\ \mathsf{Current}\ \mathsf{Devices}\ \mathsf{RCDs}\ \rightarrow\ \mathsf{Residual}\ \mathsf{Resid$







© 2023 ABB. All rights reserved.

2023/08/08

F