

PRODUCT-DETAILS

F202 A-100/0.03 AP-R F202 A-100/0.03 AP-R Residual Current Circuit Breaker 2P A type 30 mA



Extended Product Type	F202 A-100/0.03 AP-R	
Product ID	2CSF202401R1900	
EAN	8012542916505	
Catalog Description	F202 A-100/0.03 AP-R Residual Current Circuit Breaker 2P A type 30 mA	
Long Description	with some configurations for special applications. This product provides the best compromise between safety and continuity in the service, thanks to the resistance to unwanted trippings.	
Long Description	compromise between safety and continuity in the service, thanks to the resistance to	
	compromise between safety and continuity in the service, thanks to the resistance to	
Circular Value	compromise between safety and continuity in the service, thanks to the resistance to unwanted trippings.	

Environmental Product

9AKK108467A3700 Subject to change without notice

Declaration - EPD

Technical	
Standards	IEC/EN 61008 UL 1053
Type of Residual Current	A type
Rated Voltage (U _r)	230 V
Rated Operational Voltage	230 V
Rated Insulation Voltage (U _i)	500 V
Rated Impulse Withstand Voltage (U _{imp})	4 KV
Input Voltage Type	AC
Rated Current (I _n)	100 A
Rated Residual Current	30 mA
Rated Conditional Short- Circuit Current (I _{nc})	10 kA
Rated Service Short- Circuit Breaking Capacity (I _{cs})	1 kA
Maximum Surge Current	3 kA
Leakage Current Type	A
Rated Frequency (f)	50 60 Hz
Power Loss	at Rated Operating Conditions per Pole 6.5 W
Power Supply Connection	Arbitrary
Electrical Endurance	10000 cycle
Number of Poles	2
Operating Characteristic	Instantaneous (APR High Immunity)
Mounting Type	DIN-Rai
Options Provided	None
Accessories Available	Yes
Connecting Capacity	Busbar 10 mm² Rigid 35 35 mm² Flexible 35 35 mm²
Rated Cross-Section	4 - Multi-Wired 035 mm² 1 - Solid-Core 3535 mm²
Environmental	
Ambient Temperature	-2555 °C
Ambient Air Temperature	Operation -2555 °C
Degree of Protection	IP2X
Pollution Degree Resistance to Vibrations acc. to IEC 60068-2-6	2 0.1 mm or 1 g - 20 cycles at 5…150…5 Hz
Resistance to Shock acc. to IEC 60068-2-27	25g 2 shocks 13 ms
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
© 2023 ABB All rights reserved	2023/08/08 Subject to char

Subject to change without notice

F202 A-100/0.03 AP-R

RoHS Information	9AKK106713A5602
REACH Declaration	9AKK108467A9482
Environmental Information	Refer to RoHS
SCIP	18f132b0-8f03-4611-9c59-dba03cc369bf Italy (IT)
Conflict Minerals	9AKK108468A3363
Reporting Template	
(CMRT)	

Maximum Operating	277 V AC
Voltage UL/CSA	
Short-Circuit Current	30 mA
Rating (SCCR)	

Dimensions	
Width in Number of Modular Spacings	2
Product Net Width	0.035 m
Product Net Height	0.085 m
Product Net Depth / Length	0.069 m
Product Net Weight	0.200 kg
Built-In Depth (t ₂)	69 mm

Ordering	
Minimum Order Quantity	1 piece
Package Level 1 Units	box 1 piece
Package Level 1 Gross Weight	0.235 kg
Customs Tariff Number	85363030
Country of Origin	Italy (IT)

Certificates and Declarations

Declaration of Conformity	9AKK106713A5602
- CE	

Popular Downloads

Data Sheet, Technical 9AKK107991A8329 Information 9AKK107991A6127

Classifications

© 2023 ABB. All rights reserved.

ETIM 8	EC000003 - Residual current circuit breaker (RCCB)	
ETIM 9	EC000003 - Residual current circuit breaker (RCCB)	
EPLAN Catalog Tree	Electrical engineering / Protection devices / Ground fault current circuit breake	
EPLAN Function Definition	Ground fault current circuit-breaker / Ground fault current circuit breakers, 4 connection points / Ground fault current circuit breaker, two-pole 1/2 2/1 3/4 4/3	
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)	
WEEE B2C / B2B	Business To Consumer	
CN8	85363030	
UNSPSC	39121601	
eClass	V11.0 : 27142201	
IDEA Granular Category Code (IGCC)	4875 >> Residual current circuit breaker (RCCB)	
Object Classification Code	F	

Accessories	Description	Туре	Quantity	Unit Of
2CDS200912R0001	S2C-H6R Auxiliary Contact	S2C-H6R	2	Measure piece
2CDS200922R0001	S2C-S/H6R Signal / Auxiliary Contact	S2C-S/H6R	2	piece
2CDS200946R0001	S2C-H6-11R Auxiliary Contact	S2C-H6-11R	1	piece
2CDS200946R0003	S2C-H6-02R Auxiliary Contact	S2C-H6-02R	1	piece
2CDS200946R0002	S2C-H6-20R Auxiliary Contact	S2C-H6-20R	1	piece
2CSS200933R0011	F2C-A1 Shunt trip	F2C-A1	1	piece
2CSS200933R0012	F2C-A2 Shunt trip	F2C-A2	1	piece
2CSS200911R0005	S2C-UA 230 AC Undervoltage release	S2C-UA 230 AC	1	piece
2CSS200911R0007	S2C-UA 24 DC Undervoltage release S2C-UA 24 DC		1	piece
2CSS200911R0002	S2C-UA 24 AC Undervoltage release S2C-UA 24 AC		1	piece
2CSS200911R0008	S2C-UA 48 DC Undervoltage release S	S2C-UA 48 DC Undervoltage release S2C-UA 48 DC		piece
2CSS200911R0004	S2C-UA 110 AC Undervoltage release	S2C-UA 110 AC	1	piece
2CSS200911R0006	S2C-UA 400 AC Undervoltage release	S2C-UA 400 AC	1	piece
2CSS200911R0001	S2C-UA 12 DC Undervoltage release S	S2C-UA 12 DC Undervoltage release S2C-UA 12 DC		piece
2CSS200911R0010	S2C-UA 230 DC Undervoltage release	S2C-UA 230 DC	1	piece
2CSS200911R0009	S2C-UA 110 DC Undervoltage release	S2C-UA 110 DC	1	piece
2CSS200911R0003	S2C-UA 48 AC Undervoltage release S	52C-UA 48 AC	1	piece
2CSS200910R0005	S2C-OVP1 Overvoltage release	S2C-OVP1	1	piece
2CSS200993R0005	S2C-OVP2 Overvoltage release	S2C-OVP2	1	piece
2CSF200997R0013	F2C-CM Motor operating device	F2C-CM	1	piece
2CSF200996R0013	F2C-ARI Auto-reclosing unit	F2C-ARI	1	piece

Categories

Low Voltage Products and Systems \rightarrow Modular DIN Rail Products \rightarrow Residual Current Devices RCDs \rightarrow Residual Current Devices RCDs

