# Sub Miniature Rocker Switch Multicomp PRO

## RoHS Compliant



### **Specifications**

 $\begin{array}{ll} \mbox{Mechanical Life} & : 30,000 \mbox{ Make-and-Break Cycles} \\ \mbox{Contact Resistance} & : 20m\Omega \mbox{ max. Initial @ 2-4V DC} \end{array}$ 

100mA For Both Silver and Gold Plated Contacts

Insulation Resistance :  $1,000M\Omega$  min.

Dielcetric Strength : 1,000 Vrms min. @ Sea Level

Operating Temperature : -40°C to 85°C

#### Materials

Case : Diallyl phthalate (DAP) (UL94V-0)

Actuator : Nylon, Black std.


Bushing : Zinc, Nickel Plated
Housing : Stainless Steel

Switch Support : Brass, tin Plated

Terminals/Contact : Copper

	Contact Plating	Terminal Plating	Ratings	
Q	Silver	Silver	3 Amps @120V AC or 28V DC	
С	Gold over Silver	Gold over silver	1 Amps @250V AC	
R	Gold	Gold	0.4 Volt-Amps(VA) max. @20V max. (AC or DC)	





#### **Switch Function**


	Pos.1	Pos.2	Pos.3
Model No.			
MP4MS1R102M7RES	ON	NONE	ON
Term. Comm.	2-3		2-1
Schematic	1 0 2 Comm. 3	N/A	2 Comm. 9 3

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro



# Sub Miniature Rocker Switch Multicomp PRO

### **Diagram**



Dimensions: Inches (Millimetres)

#### **Part Number Table**

Description	Part Number	
Rocker Switch, Vertical Right angle, PC terminal	MP4MS1R102M7RES	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

