Miniature Toggle Switches multicomp PRO

RoHS Compliant



Specifications

Mechanical Life : 100,000 make-and-break cycles DC 10V & 0.1ma.

 $\begin{tabular}{ll} Contact Resistance & : $10m\Omega$ max. \\ Insulation Resistance & : $500V 500M\Omega$ min. \\ \end{tabular}$

Dielectric Strength : 1,000 Vrms min.@sea level.

Operating Temperature : -40°C to 85°C.


Materials


Case : Diallyl phthalate (DAP) (UL94V-0)

Actuator : Brass, Chrome Plated
Bushing : Brass, Nickel Plated
Housing : Stainless Steel

Terminal/Contact : Brass

Diagram





Dimensions: Inches (Millimetres)

	Contact Plating	Terminal Plating	Ratings	
Q	Silver	Slver	6A @ 125V AC	
С	Gold over Silver	Gold over silver	3A @ 250V AC or 28V DC	
R	Gold	Gold	0.4 Volt-Amps (VA) max. @20V max. (AC or DC)	

Switch Function

	Pos.1	Pos.2	Pos.3
Model	À	•	.
MP1FD2T1B6M2QES-5	ON	NONE	(ON)
Term. Comm.	2-3, 5-6		2-1, 5-4
Schematic	2 Comm. 3	N/A	2 Comm. 3
Concinatio	5 Comm. 6		5 Comm. 6


Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro



19/04/24 V1.0

Miniature Toggle Switches multicomp PRO





Part Number Table

Description	Part Number	
Toggle Switch, On-None-(On), PC mount	MP1FD2T1B6M2QES-5	

Dimensions: Inches (Millimetres)

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

