

# Palm Size Digital Multimeter



## Features

- 2000 Count Display
- Manual Function Select & Auto Ranging
- Diode Test & Continuity Buzzer
- Transistor Test
- Data Hold
- LCD Display
- Auto Power Off
- Low Battery Indication
- Input Impedance for DC Voltage: Around 10MΩ

## Electrical Specifications

Basic Functions	Range	Best Accuracy
DC Voltage	200mV/2000mV/20V/200V/600V	±(0.5%+2)
AC Voltage	200V/600V	±(1.2%+3)
DC Current	2,000μA/20mA/200mA/10A	±(1%+2)
Resistance	200Ω/2000Ω/20kΩ/200kΩ/2000kΩ/20MΩ	±(0.8%+5)
Temperature (°C)	-40°C to 1,000°C	±(1.0%+3)

## General Characteristics

Safety Rating	: CAT III 600V
Power	: 9V Battery (6F22)
LCD Size	: 49mm × 18mm
Product Colour	: Orange & Grey
Product Weight	: 200g
Product Size	: 72mm × 137mm × 35mm

Accessories	Qty.	Note
Operating Manual	1 piece	-
Test Leads	1 pair	Leads length: 900mm, Rod length: 115mm Tip length: 18mm Safety level: CAT III 1000V/CAT IV 600V 10A
Temp Probe	1 piece	Crosshead socket type thin line 1 m K-type -50°C to +260°C

## Part Number Table

Description	Part Number
Palm Size Digital Multimeter	72-10390A

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. TENMA is the registered trademark of Premier Farnell Limited 2019.

Newark.com/exclusive-brands  
Farnell.com/exclusive-brands  
Element14.com/exclusive-brands

