Single Channel Programmable DC Power Supply





Specifications Table

Performance		72-2940	
Channels		Single Channel Programmable	
AC Input Voltage		230V ±10% / 50Hz	
Output Voltage Range		0 - 60V	
Output Current Range		0 - 5A	
Load Regulation	Voltage	≤0.01% + 2mV	
	Current	≤0.1% + 10mA	
Line Regulation	Voltage	≤0.01% + 3mV	
	Current	≤0.1% + 3mA	
Setup Resolution	Voltage	10mV	
	Current	1mA	
Setup Accuracy (25°C ±5°C)	Voltage	≤0.5% + 30mV	
	Current	≤0.5% + 5mA	
Ripple (20Hz - 20MHz)	Voltage	≤1m Vrms	
	Current	≤3m Arms	
Temperature Coefficient	Voltage	≤150ppm + 10mV	
	Current	≤150ppm + 5mA	
Read Back Accuracy	Voltage	10mV	
	Current	1mA	
Read Back Temperature Coefficient	Voltage	≤150ppm + 10mV	
	Current	≤150ppm + 5mA	
Reaction Time (10% Rated load)	Voltage Rise	≤100ms	
	Current Drop	≤100ms	
Interfaces		RS-232, USB	
Weight		8kg	
Dimension (W x H x D)		110mm × 156mm × 300mm	
Accessories		User manual	
		Power cord	UK plug + EU plug, Diameter: 0.75mm² × 3, length: 1.2m
		USB cable	USB cable length 1.5m, USB2, AM to BM

Part Number Table

Description	Part Number
Single Channel DC Power Supply, Programmable, 300W	72-2940

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage arisingly is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. TENMA is the registered trademark of Premier Farnell Limited 2019.

Newark.com/exclusive-brands Farnell.com/exclusive-brands Element14.com/exclusive-brands

