Bench Top Power Supply Single Channel







Main Characteristics

RoHS Compliant

- · Complete digital control
- 10 mV / 1 mA high accuracy & resolution
- · Low noise and ripple
- Constant voltage (CV) and constant current (CC) modes
- Adjustable over current protection (OCP) and over voltage protection (OVP)
- 5 store and recall memory settings
- · Output switch control
- Power-off memory function

Specifications

Parameter	Voltage	Current	
Output Rating	0V to 30V	0A to 5A	
Load Regulation	≤0.01% +2mv	≤0.1% +10mA	
Line Regulation	≤0.01% +3mv	≤0.1% +3mA	
Setup Resolution	10mV	1mA	
Setup Accuracy (25°C ±5°C)	≤0.5% +20mV	≤0.5%+10mA	
Ripple(20Hz to 20MHz)	≤2mV rms	≤3mA rms	
Temp. Coefficient	≤150ppm	≤150ppm	
Read Back Accuracy	10mV	1mA	
Read Back Temp. Coefficient	≤150ppm	≤150ppm	
Reaction Time (10% Rated load)	≤100mS	≤100mS	
Operation Environment : Indoor use	Altitude: ≤ 2000m, Ambient temperature : 0°C to +40°C Relative humidity: ≤ 80%		
Supply Voltage	230V ±10% 50Hz		
Weight and Dimension	4.3kgs / 110mm (W) ×156mm (H) × 260mm (D)		
Storage Environment	Ambient temperature: -10°C to +70°C Relative humidity: ≤ 70%		
Standard Warranty	12 Months		
Accessories	User manual		
Accessories	Power cord	UK plug + EU plug, Diameter: 0.75mm² × 3, length: 1.2m	

Part Number Table

Note: Test Leads not included

	Description	Part Number
I	Bench Top Power Supply, Single Channel, 0V to 30V, 0A to 5A	MP710503

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

